

Table 1: Bill of materials

Item	Q.ty	Ref.	Part/Value	Description	Manufacturer	Order code
1	3	C1, C6, C75	1 μ F, 0603	Capacitors	AVX	0603ZG105ZAT2A
2	6	C2, C4, C7, C67, R82, C82	10 nF, 0603	Capacitors	AVX	06033C103KAT2A
3	15	C3, C5, C26, C30, C48, C56, C57, C59, C62, C70, C72, C83, C84, C85, C86	100 nF, 0603	Capacitors	AVX	06033G104ZAT2A
4	2	C8, C87	1 μ F, 0603	Capacitor	TDK	C1608X5R1H105K080AB
5	1	C15	10 μ F, 0805	Capacitor	Murata	GRM21BR61E106KA73L
6	1	C16	1 nF, 0603 - N.M.	Capacitor		
7	1	C17	100 nF, 0603 - N.M.	Capacitor		
8	1	C18	100 nF, 0805 - N.M.	Capacitor		
9	1	C25	1 μ F, 0603 - N.M.	Capacitor		
10	1	C27	100 nF, 0805	Capacitor	AVX	06033G104ZAT2A
11	2	C28, C81	150 nF, P15L6	Capacitors	EPCOS	B32922C3154K
					Würth Elektronik	890334025022CS
12	2	C29, C79	10 μ F, R13H20-P5	Capacitors	Rubycon	350BXC10MEFC10X20
13	2	C34, C80	680 pF, 0603	Capacitors	KEMET	C0603C681J5GACTU
14	2	C36, C37	1 nF, C1210	Capacitors	AVX	1210GC102KAT1A
15	2	C39, C42	1 nF, 1206	Capacitors	KEMET	C1206C102KDRACU
16	2	C40, C88	470 nF, 175X100X165-P15	Capacitors	Vishay	BFC233920474
					Würth Elektronik	890334025039CS
17	1	C41	330 nF, 175X85X150-P15	Capacitor	Vishay	2222 339 20334
					Würth Elektronik	890334025034CS
18	1	C43	22 μ F, R16H21-P75	Capacitor	Panasonic	EEUEE2W220S
19	1	C44	220 pF, 1206	Capacitor	AVX	1206AA221KAT1A
20	2	C46, C60	1 nF, 0603	Capacitors	AVX	06035C102KAT2A
21	1	C47	100 pF, 0603	Capacitor	KEMET	C0603C101J5GACTU
22	1	C49	2.2 nF, 0603	Capacitor	Vishay	VJ0603Y222KNAAO
23	1	C51	3.3 μ F, R10HXX-P5	Capacitor	Rubycon	450PK3R3MEFC8X11.5
24	1	C52	150 nF, 0603	Capacitor	Murata	GRM188R71E154KA01D
25	1	C53	22 nF, 0603	Capacitor	AVX	06035C223KAT2A
26	1	C54	1.5 nF, 0603	Capacitor	KEMET	C0603C152K1RACTU
27	2	C55, C58	1 μ F, 0805	Capacitors	Murata	GCM21BR71E105KA56L
28	1	C61	22 μ F, 1206	Capacitor	KEMET	C1206C226M8PACTU
29	1	C63	10 μ F, r5h11-p25	Capacitor	Panasonic	ECEA1EKS100

Item	Q.ty	Ref.	Part/Value	Description	Manufacturer	Order code
30	1	C65	100 pF, 0603 - N.M.	Capacitor		
31	1	C66	6.8 nF, 0603	Capacitor	Kemet	C0603C682K5RACTU
32	1	C71	1 nF, 0805	Capacitor	KEMIT	C0805C102J5GACTU
33	1	C73	1 nF, 850X800-175	Capacitor	MURATA	DEBB33F102KN3A
34	1	C76	1 µF, r5h11-p25	Capacitor		
35	1	C77	1 µF, 0805	Capacitor		
36	1	C78	220 nF, 0603	Capacitor	TDK	C1608X7R1H224K080AB
38	1	C89	47 µF, R16H21- P75 - N.M.	Capacitor	Panasonic	EEUEE2V470
39	1	C90	10 µF, 0805	Capacitor	Murata	GRM219R61E106KA12D
40	3	C91, C95, C96	100 nF, 0603	Capacitors	AVX	06033G104ZAT2A
41	1	C92	10 nF, 0603	Capacitor	AVX	06033C103KAT2A
42	2	C93, C94	47 pF, 0603	Capacitors	Kemet	C0603C470J5GACTU
43	1	D1	FAULT, 0603	LED	OSRAM Opto Semiconductors	LS Q976
44	1	D2	RUN, 0603	LED	OSRAM Opto Semiconductors	LT Q39G-Q1S2-25-1
45	1	D3	5.6 V, SOT23	Diode	DiodesZetex	BZX84C5V6-7-F
46	2	D4, D36	STTH3R06	TURBO 2 ultrafast high voltage rectifier	ST	STTH3R06
47	1	D7	B6S-E3/80	PONTE- SMD-MBXS	Vishay	B6S-E3/80
48	1	D8	15 V-N.M.	POWERDI323		
49	1	D10	STTH1L06	TURBO 2 ultrafast high voltage rectifier	ST	STTH1L06U
50	1	D11	MMSD4148T1G	SOD123	ONSemiconductors	MMSD4148T1G
51	2	D12, D37	STTH3R06	TURBO 2 ultrafast high voltage rectifier	ST	STTH3R06S
52	2	U3, D13	B6S-E3/80	PONTE- SMD-MBXS	Vishay	B6S-E3/80
53	2	D14, D30	MMSD4148T1G	SOD123	ONSemiconductors	MMSD4148T1G
54	1	D23	1N4007	DIODO-SMA	DiodesZetex	S1J-13-F
55	1	D24	GBU8K-E3/45	KBU8XXG	Taiwan Semiconductor	KBU807G T0
56	1	D25	STTH5L06	TURBO 2 ultrafast high voltage rectifier	ST	STTH5L06B-TR
57	1	D26	LL4148	sod80	Vishay	LL4148-GS18
58	1	D27	5.6 V, SOD123 - N.M.	Diode	DiodesZetex	BZT52C5V6-7-F
59	1	D28	1N4007, SMA	Diode	DiodesZetex	S1J-13-F

Item	Q.ty	Ref.	Part/Value	Description	Manufacturer	Order code
60	2	D31, D33	STTH1L06A	TURBO 2 ultrafast high voltage rectifier	ST	STTH1L06A
61	1	D32	16 V, SMA	Diode	Vishay	SML4745-E3
62	1	D34	BAT54J, SOD323	Small signal Schottky diode	ST	BAT54J
63	2	D38, D39	LL4148, SOD123	Diodes	ONSemiconductors	MMSD4148T1G
64	1	D40	12 V, SOD123	Diode	DiodesZetex	DDZ9699-7
65	1	D41	MMSZ5V1T1G, SOD123	Diode	ONSemiconductors	MMSZ5V1T1G
66	2	D42, D43	STTH3R06	TURBO 2 ultrafast high voltage rectifier	ST	STTH3R06S
67	1	D44	BAT54J, SOD323	Diode	ST	BAT54J
68	1	D45	BAV102, SOD80	Diode	Nexperia	BAV102-GS08
69	1	D47	YELLOW, 0805	LED	Lumex	SML-LXT0805YW-TR
70	7	TP22, TP23, TP24, TP25, TP31, TP32, EARTH	TP	Test points	Keystone Electronics	5013
71	1	F1	pth-r85h80-p5	Fuse	Wickmann	3701400000
72	1	HS1	LS205-RS2342328	Heatsink	Any	Heatsink for Q12 and D24
73	1	ISO1	FOD817AS	OPTO-SOP254P-1050X46	Fairchild Semiconductor	FOD817AS
74	1	ISO2	PC357N14J00F	OPTO-SOP254P-700X210-NO25	SHARP	PC357N14J00F
75	1	JP5	JUMPER	JP3SO	Any	Any
76	1	JP6	JUMPER	JP2SO	Any	Any
77	1	JP7	JUMPER 0 R RES	RESC-1206	Any	Any
78	1	J1	SWIM I/F	STRIP254P-M-4	Any	Any
79	1	J3	DALI	MOR-2POLI-WAGO-250-402	WAGO	250-402
80	1	J4	CH0	MOR-2POLI-WAGO-250-402	WAGO	250-402
81	1	J8	HEADER 3	MOR-3POLI-508	TE Connectivity	282837-3
82	1	J9	0-10V	MOR-2POLI-WAGO-250-402	WAGO	250-402
83	1	J47	CON-1x6	STRIP254P-M-6	Any	Any
84	1	J48	10104110-0001LF	MICRO_USB-B-10104110	Amphenol FCI	10104110-0001LF
85	3	L1, L10, L11	WE-CBF	Ferrite beads	Würth Elektronik	74279262
86	5	L2, L3, L4, L5, L6	WE-CBF	Ferrite beads	Würth Elektronik	74279269

Item	Q.ty	Ref.	Part/Value	Description	Manufacturer	Order code
87	1	L8	2.2 mH, R75H92-P3	Inductor	Itacoil	SLD0608222
88	1	L9	220 µH	Inductor	Würth Elektronik	7447060
89	1	L12	120 R	Inductor	Würth Elektronik	74279262
90	2	P400V, PGND	1 mm	Test point	Keystone Electronics	5001
91	1	Q1	STN93003, SOT223	High voltage fast switching PNP power transistor	ST	STN93003
92	1	Q2	BC857C	PNP transistor	Nexperia	BC857C
93	1	Q3	STN1HNK60, SOT223	N-channel 600 V, 7.3 Ohm typ., 1 A SuperMESH Power MOSFET	ST	STN1HNK60
94	2	Q4, Q5	STD16NF25, DPAK	N-channel 250 V, 0.195 Ohm, 14 A STRipFET II Power MOSFET	ST	STD16NF25
95	2	Q10, Q11	STD13N60M2, DPAK	N-channel 600 V, 0.35 Ohm typ., 11 A MDmesh M2 Power MOSFET	ST	STD13N60M2
96	1	Q12	STF18N60M2	N-channel 600 V, 0.255 Ohm typ., 13 A MDmesh M2 Power MOSFET	ST	STF18N60M2
97	2	Q13, Q14	BC857CW	Bipolar transistor	Infineon	BC 857CW
98	1	Q15	BFN18-N.M.	SOT89	Any	Any
99	1	RT1	PTC	Mountable PTC resettable fuse	Bourns	MF-NSMF012-2
100	1	RV1	B72210, SIOV- S10K300	Varistor	EPCOS	B72210S0301K101
101	1	RV2	2R5	Thermistor	EPCOS	B57237S259M
102	6	R1, R2, R48, R72, R76, R116	1 K, 0603	Resistors	Vishay	CRCW06031K00FKEA
103	1	R3	9K1, 0603	Resistor	Panasonic	ERJPA3F9101V
104	1	R4	5K6, 0603	Resistor	Vishay	CRCW06035K60FKEA
105	1	R15	4.3 K, 0603	Resistor	Vishay	CRCW06034K30FKEA
106	3	R16, R18, R21	68 K, 0603	Resistors	Any	Any
107	1	R17	390 R, 0603	Resistor	Any	Any
108	1	R19	1 R, 900X320- P15-1W2	Resistor	Ohmite	OL10G5E
109	2	R20, R106	1.2 K, 0603	Resistors	Any	Any

Item	Q.ty	Ref.	Part/Value	Description	Manufacturer	Order code
110	1	R22	4.7 K, 0603	Resistor	Any	Any
111	1	R23	2K2, 0603-N.M.	Resistor		
112	1	R26	47 K, 0805 - N.M.	Resistor		
113	2	R27, R30	10 R, 0805	Resistors	Bourns	CR0805-FX-10R0GLF
114	1	R28	12 K, 0603	Resistor	Any	Any
115	1	R29	3.9 K, 0603	Resistor	Any	Any
116	1	R34	220 R, 0603	Resistor	Any	Any
117	2	R36, R37	2R4	Resistors	Panasonic	ERJ1TRQF2R4U
118	3	R40, R47, R53	330 K, 1206	Resistors	TE Connectivity	CRGH1206J330K
119	6	R41, R42, R43, R46, R52, R55	2M2, 1206	Resistors	Vishay	CRCW12062M20FKEA
120	2	R44, R58	18 K, 1206	Resistors	Vishay	CRCW120618K0FKEA
121	2	R45, R59	10 R , 0805 - N.M.	Resistors	Bourns	CR0805-FX-10R0GLF
122	2	R49, R50	0R39, 2512	Resistors	Panasonic	ERJ1TRQFR39U
123	1	R54	68 K, 0603 - N.M.	Resistor		
124	1	R56	10 K, 0603 - N.M.	Resistor		
125	1	R57	10 R, 0805	Resistor	Bourns	CR0805-FX-10R0GLF
126	1	R60	27 K, 0603	Resistor	Any	Any
127	1	R61	10 K, 0603	Resistor	Bourns	CR0603-FX-1002HLF
128	5	R62, R75, R77, R97, R99	12 K, 0603	Resistors	Vishay	CRCW060312K0FKEA
129	1	R64	N.M.	Resistor		
130	1	R65	10 K, 0805	Resistor	Any	Any
131	1	R67	33 K, 1206	Resistor	Vishay	CRCW120633K0FKEA
132	1	R71	12 K, 0603	Resistor	Kemet	C0805C102J5GACTU
133	2	R74, R78	2.2 K, 0603	Resistor	Vishay	CRCW06032K20FKEA
134	2	R83, R86	100 R, 0805	Resistors	Any	Any
135	2	R84, R85	100 K, 0603	Resistors	Any	Any
136	2	R88, R93	1 M, 1206	Resistors	TE Connectivity	CRG1206F1M0
137	1	R89	24 K, 0603	Resistor	Any	Any
138	1	R90	18 K, 0603	Resistor	Any	Any
139	1	R91	510 R, 0603	Resistor	Any	Any
140	1	R92	56 K, 0603	Resistor	Any	Any
141	1	R94	680 R, 0805	Resistor	Any	Any
142	1	R95	47 K, 0805	Resistor	Any	Any
143	1	R96	150 K, 0603	Resistor	Vishay	CRCW0603150KFKEA
144	1	R98	22 K, 0603	Resistor	Vishay	CRCW060322K0FKEA
145	1	R100	16 K, 0603	Resistor	Vishay	CRCW060316K0FKEA
146	1	R101	220 R, 0603	Resistor	Vishay	CRCW0603220RFKEA

Item	Q.ty	Ref.	Part/Value	Description	Manufacturer	Order code
147	1	R102	0 R, 1206	Resistor	Any	Any
148	2	R103, R104	10 K, 0603	Resistor	Any	Any
149	1	R105	8.2 K, 0603	Resistor	Any	Any
150	1	R107	10 K, 0603	Resistor	Any	Any
151	1	R108	22 R, 0603	Resistor	Any	Any
152	2	R109, R110	330 R, 0603	Resistors	Any	Any
153	1	R111	10 K, 0603	Resistor	Any	Any
154	2	R112, R117	0 R, 0603	Resistors	Any	Any
155	1	R113	1 K, 0603	Resistor	Any	Any
156	1	R114	47 K, TRIMM-100X50X110 W	Resistor	Any	Any
157	1	R115	57 K, 1206	Resistor	Any	Any
158	1	SW1	TL1015	Switch button	E-Switch	TL1015BF160QG
159	22	TP3, TP5, TP6, TP8, TP9, TP10, TP18, TP19, TP20, TP21, TP36, TP37, TP38, TP39, TP40, TP41, TP42, TP43, TP44, TP45, TP47, TP48	TPSMD-50RD	Test points	Any	Any
160	3	TP33, TP34, TP35	TPSMD-50RD	Test points	Any	Any
161	1	TP46	TPSMD-50RD	Test points	Any	Any
162	1	T1	TLLE20D01	Transformer	Itacoil	TLLE20D01
163	1	T2	TSLETD3402	Transformer	Itacoil	TSLETD3402
164	1	T5	10 mH	Inductor	Itacoil	SCLE25103
					Würth Elektronik	750317193
165	1	T6	429 µH- SMC037-100113	Transformer	Itacoil	TCLPQ262501
166	1	T7	SMLEP1303	Transformer	Itacoil	SMLEP1303
					Würth Elektronik	750510810
167	1	U1	STLUX385A, TSSOP050P-640X120	Digital controller for lighting and power conversion applications	ST	STLUX385ATR
168	1	U4	ACPL- M61L-000E-SOP127P-700X210- N.M.	OPTO- NO2	Any	Any
169	1	U5	L6398D-N.M.SOP127P-600X168		Any	Any
170	1	U10	L6388ED, SOP127P-600X168	HV high and low side driver with embedded bootstrap diode	ST	L6388ED
171	1	U11	PM8841D, SOT23-6	Single channel low-side gate driver	ST	PM8841D

Item	Q.ty	Ref.	Part/Value	Description	Manufacturer	Order code
172	1	U12	VIPer06XS, SSOP100P-620X175-	VIPerPlus family: energy saving high voltage converter for direct feedback	ST	VIPER06XSTR
173	1	U13	LK112M33TR, SOT23-5	Low noise and low drop voltage regulator with shutdown function	ST	LK112M33TR
174	2	U14, U15	ACPL-M61L-000E, SOP127P-700X210-NO2	Optocoupler	Broadcom	ACPL-M61L-000E
175	1	U16	PM8841D, SOT23-6	Single channel low-side gate driver	ST	PM8841D
176	1	U17	LD2980CM50TR, SOT23-5	Ultra low drop voltage regulators compatible with low ESR output capacitors	ST	LD2980CM50TR
177	1	U18	TS3021ICT, SC70-5	Rail-to-rail 1.8 V high-speed comparator	ST	TS3021ICT
178	1	U19	STLM20W87F, SOT323-5	Ultra-low current, 2.4 V, high precision analog temperature sensor	ST	STLM20W87F
179	1	U20	FT232R, SSOP065P-820X200	USB to serial UART interface	FTDI	FT232RL

STMicroelectronics**EVALUATION BOARD LICENSE AGREEMENT**

By using this evaluation board or kit (together with all related software, firmware, components, and documentation provided by ST, "Evaluation Board"), You ("You") are agreeing to be bound by the terms and conditions of this Evaluation Board License Agreement ("Agreement"). Do not use the Evaluation Board until You have read and agreed to this Agreement. Your use of the Evaluation Board constitutes Your acceptance of this Agreement.

LICENSE

STMicroelectronics ("ST") grants You the right to use the enclosed Evaluation Board offering limited features only to evaluate and test ST products solely for Your evaluation and testing purposes in a research and development setting. The Evaluation Board shall not be, in any case, directly or indirectly assembled as a part in any production of Yours as it is solely developed to serve evaluation purposes and has no direct function and is not a finished product. If software and/or firmware is accompanied by a separate end user license agreement ("EULA"), then such software and/or firmware shall be governed by such EULA.

EVALUATION BOARD STATUS

The Evaluation Board offers limited features allowing You only to evaluate and test the ST products. The Evaluation Board is not intended for consumer or household use. You are not authorized to use the Evaluation Board in any production system, and it may not be offered for sale or lease, or sold, leased or otherwise distributed for commercial purposes. If the Evaluation Board is incorporated in an evaluation system, the evaluation system may be used by You solely for Your evaluation and testing purposes. Such evaluation system may not be offered for sale or lease or sold, leased or otherwise distributed for commercial purposes and must be accompanied by a conspicuous notice as follows: "This device is not, and may not be, offered for sale or lease, or sold or leased or otherwise distributed for commercial purposes".

OWNERSHIP AND COPYRIGHT

Title to the Evaluation Board remains with ST and/or its licensors. You may not remove any copyright or other proprietary rights notices without prior written authorization from ST. You may make one copy of the software and/or firmware of the Evaluation Board for back up or archival purposes provided that You reproduce and apply to such copy any copyright or other proprietary rights notices included on or embedded in the software and/or firmware. You agree to prevent any unauthorized copying in whole or in part of the Evaluation Board.

RESTRICTIONS AND WARNINGS

Before You handle or use the Evaluation Board, you must carefully review any related documentation provided by ST. Such documentation may contain important warnings. You shall comply with all such warnings and other instructions and employ reasonable safety precautions in using the Evaluation Board. Failure to do so may result in death, personal injury, or property damage. If You have any questions regarding the safe usage of the Evaluation Board, You should contact ST for guidance. You may not sell, assign, sublicense, lease, rent or otherwise distribute the Evaluation Board for commercial purposes, in whole or in part, or use Evaluation Board in a production system, with the exception that if You are an authorized ST distributor, you may resell the Evaluation Board in compliance with the applicable terms and conditions. Except as provided in this Agreement or as explicitly permitted in the documentation of the Evaluation Board, You may not reproduce the Evaluation Board or modify, reverse engineer, de-compile or disassemble its software and/or firmware, in whole or in part. You shall not use the Evaluation Board in any safety critical or functional safety testing, including but not limited to testing of life supporting, military or nuclear applications. ST expressly disclaims any responsibility for such usage which shall be made at Your sole risk, even if ST has been informed in writing of such usage. Unless expressly designated in writing by ST as suitable for use in testing automotive or aerospace applications, You shall not use the Evaluation Boards in such testing. According to European Semiconductor Industry Association (ESIA) letter, "ESIA Response on WEEE Review (May 2008) of the Directive 2002/96/EC on Waste Electrical and Electronic Equipment (WEEE)"; Semiconductor products and evaluation and demonstration boards are not in the scope of the Directive 2002/96/EC of the European Parliament and of the Council on waste electrical and electronic equipment (WEEE). Consequently aforementioned products do not have to be registered nor are they subject to the subsequent obligations.

Notice applicable to Evaluation Boards not FCC-Approved

This kit is designed to allow:

1. Product developers to evaluate electronic components, circuitry, or software associated with the kit to determine whether to incorporate such items in a finished product and
2. Software developers to write software applications for use with the end product.

This kit is not a finished product and when assembled may not be resold or otherwise marketed unless all required FCC equipment authorizations are first obtained. Operation is subject to the condition that this product not cause harmful interference to licensed radio stations and that this product accept harmful interference. Unless the assembled kit is designed to operate under part 15, part 18 or part 95 of 47 CFR, Chapter I ("FCC Rules"), the operator of the kit must operate under the authority of an FCC license holder or must secure an experimental authorization under part 5 of this chapter.

For Evaluation Boards annotated as FEDERAL COMMUNICATIONS COMMISSION (FCC) Part 15 Compliant

- **FCC Interference Statement for Class A Evaluation Boards:** This equipment has been tested and found to comply with the limits for a Class A digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference when the equipment is operated in a commercial environment. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instruction

manual, may cause harmful interference to radio communications. Operation of this equipment in a residential area is likely to cause harmful interference in which case the user will be required to correct the interference at his own expense.

- **FCC Interference Statement for Class B Evaluation Boards:** This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:
 - Reorient or relocate the receiving antenna.
 - Increase the separation between the equipment and receiver.
 - Connect the equipment to an outlet on a circuit different from that to which the receiver is connected.
 - Consult the dealer or an experienced radio/TV technician for help.
- This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation. Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

WARRANTY

ST WARRANTS THAT IT HAS THE RIGHT TO PROVIDE THE EVALUATION BOARD TO YOU. THIS WARRANTY IS PROVIDED BY ST IN LIEU OF ALL OTHER WARRANTIES, WRITTEN OR ORAL, STATUTORY, EXPRESS OR IMPLIED, INCLUDING ANY WARRANTY AS TO MERCHANTABILITY, NON-INFRINGEMENT, FITNESS FOR ANY PARTICULAR PURPOSE, OR UNINTERRUPTED OR ERROR-FREE OPERATION, ALL OF WHICH ARE EXPRESSLY DISCLAIMED. THE EVALUATION BOARD IS PROVIDED "AS IS".

YOU WARRANT TO ST THAT YOU WILL ENSURE THE EVALUATION BOARD IS USED ONLY BY ELECTRONICS EXPERTS WHO UNDERSTAND THE DANGERS OF HANDLING AND USING SUCH ITEMS, YOU ASSUME ALL RESPONSIBILITY AND LIABILITY FOR ANY IMPROPER OR UNSAFE HANDLING OR USE OF THE EVALUATION BOARD BY YOU, YOUR EMPLOYEES, AFFILIATES, CONTRACTORS, AND DESIGNEES.

LIMITATION OF LIABILITIES

IN NO EVENT SHALL ST BE LIABLE TO YOU, WHETHER IN CONTRACT, TORT (INCLUDING NEGLIGENCE), STRICT LIABILITY, OR ANY OTHER LEGAL THEORY, FOR ANY INDIRECT, SPECIAL, CONSEQUENTIAL, INCIDENTAL, PUNITIVE, OR EXEMPLARY DAMAGES WITH RESPECT TO ANY MATTERS RELATING TO THIS AGREEMENT, REGARDLESS OF WHETHER ST HAS BEEN ADVISED OF THE POSSIBILITY OF THE SAME. IN NO EVENT SHALL ST'S LIABILITY ARISING OUT OF THIS AGREEMENT IN THE AGGREGATE EXCEED THE AMOUNT PAID BY YOU UNDER THIS AGREEMENT FOR THE PURCHASE OF THE EVALUATION BOARD, OR TEN UNITED STATES DOLLARS (\$10.00) IF NO PURCHASE PRICE WAS PAID.

INDEMNIFICATION

You shall, at Your expense, defend ST and its Affiliates against a claim or action brought by a third party for infringement or misappropriation of any patent, copyright, trade secret or other intellectual property right of a third party to the extent resulting from (1) Your combination of the Evaluation Board with any other component, system, software, or firmware, (2) Your modification of the Evaluation Board, or (3) Your use of the Evaluation Board in a manner not permitted under this Agreement. You shall indemnify ST and its Affiliates against and pay any resulting costs and damages finally awarded against ST or its Affiliates or agreed to in any settlement, provided that You have sole control of the defense and settlement of the claim or action, and ST cooperates in the defense and furnishes all related evidence under its control at Your expense. ST will be entitled to participate in the defense of such claim or action and to employ counsel at its own expense.

"Affiliates" means any corporation or other entity directly or indirectly controlled by, controlling or under common control with the entity in question, for so long as such ownership exists. "Control" means the direct or indirect beneficial ownership of more than fifty (50%) percent of the stock or other equity interests entitled to vote for the election of directors or an equivalent governing body. Any such corporation or other legal entity shall be deemed to be an Affiliate of such Party only as long as such Control exists.

TERMINATION

ST may terminate this Agreement without notice if You breach this Agreement. Upon termination, You shall immediately destroy or return all copies of the software, firmware, and documentation of the Evaluation Board to ST and certify in writing to ST that You have done so.

APPLICABLE LAW AND JURISDICTION

This Agreement shall be governed, construed and enforced in accordance with the laws of Switzerland, without regard to its conflict of laws rules. The UN Convention on Contracts for the International Sale of Goods shall not apply to this Agreement. In case of dispute and in the absence of an amicable settlement, the only competent jurisdiction shall be the Courts of Geneva, Switzerland. Any breach of this Agreement by You may result in irreparable damage to ST for which ST will not have an adequate remedy at law. Accordingly, in addition to any other remedies and damages available, You acknowledge and agree that ST may immediately seek enforcement of this Agreement in any jurisdiction by means of specific performance or injunction, without any requirement to post a bond or other security.

**SEVERABILITY**

If any provision of this agreement is or becomes, at any time or for any reason, unenforceable or invalid, no other provision of this agreement shall be affected thereby, and the remaining provisions of this agreement shall continue with the same force and effect as if such unenforceable or invalid provisions had not been inserted in this Agreement. In addition, any unenforceable or invalid provision shall be deemed replaced by a provision that is valid and enforceable and that comes closest to expressing the intention of the unenforceable or invalid provision.

WAIVER

The waiver by either party of any breach of any provision of this Agreement shall not operate or be construed as a waiver of any other or a subsequent breach of the same or a different provision.

RELATIONSHIP OF THE PARTIES

Nothing in this Agreement shall create, or be deemed to create, any joint venture, partnership, principal-agent, employer-employee or other relationship between the Parties, except that of independent contractors. Neither Party has the authority or power to bind, to contract in the name of, or to create a liability for the other in any way or for any purpose.

SURVIVAL

Any provision of this Agreement which imposes an obligation after termination of this Agreement shall survive the termination of this Agreement.

SECTION HEADINGS

Section headings are inserted for convenience only and shall not be used to interpret this Agreement.

RECYCLING

The Evaluation Board is not to be disposed as an urban waste. At the end of its life cycle, differentiated waste collection must be followed, as stated in the directive 2002/96/EC. In all the countries belonging to the European Union (EU Dir. 2002/96/EC) and those following differentiated recycling, the Evaluation Board is subject to differentiated recycling at the end of its life cycle, therefore: It is forbidden to dispose the Evaluation Board as an undifferentiated waste or with other domestic wastes. Consult the local authorities for more information on the proper disposal channels. It is mandatory to sort the Evaluation Board and deliver it to the appropriate collection centers, or, when possible, return the Evaluation Board to the seller. An incorrect Evaluation Board disposal may cause damage to the environment and is punishable by the law.