



life.augmented

# List of software parameters to check in case of switch:

## From M24C32S-FCU to M24128X-FCU

P.PORTELLI



Application Engineer

MDG/MeMorY Division

Oct 30,2020

- This document provides a list of software parameters to check in case of switch from M24C32S-FCU to M24128X-FCU.

# List of software parameters to check

Parameter	M24C32S-FCU	M24128X-FCU	Action needed	Remarks
Datasheet	 M24C32S-FCU	 M24128X-FCU	FYI	Available on ST.COM web site : - <a href="#">M24C32S-FCU</a> - <a href="#">M24128X-FCU</a>
Max address	0FFFh	3FFFh	Yes	If the application uses the sequential read instruction, on the M24128X the next address after 0FFFh will be 1000h and roll over will continue up to 3FFFh. After 3FFFh, the next address pointed will be 0000h. Read & write command must take in account the A13 MSB address.
Chip enable address	Fixed : 001	Default : 000	Yes	At factory delivery not compatible but M24128X offers the configurable chip enable address C2,C1,C0 (factory delivery value = 000). The chip enable address (C2,C1,C0) can be modified in the chip enable register. The register can be written & read with specifics command "write chip enable register" & "read chip enable register".
Software Write Protect register	Available (Protection by quarter)	Available (Protection of full plan)	Yes	M24C32S offers the software write protection by <u>quarter</u> with the <i>write protect register</i> . M24128X offers the software write protection on the <u>entire</u> memory(not by quarter) with <i>the chip enable register</i> . Same address for both register (1xxx.xxxx.xxxx.xxxx) On M24128X, the software write protection is managed by SWP bit only. When SWP=0, the memory is not protected against update. When SWP=1 the memory is fully protected against update. Updating the SWP to a new value is a reversible action.
Chip enable register management	Not Available	Available	Yes	With the M24128X, the user writes & reads the <i>chip enable register</i> with the specific commands "write chip enable register" & "read chip enable register". Can be updated: - The C2,C1,C0 bits for the chip enable address - The SWP bit for the protection of the memory array

## CONFIDENTIALITY OBLIGATIONS:

This document contains confidential information

It is classified ST Confidential and its distribution is submitted to ST Authorization

Disclosure of this document to any non authorized party must be previously authorized by ST only under the provision of a signed NDA between ST and Customer and must be treat as strictly confidential.

Information in this document is provided solely in connection with ST products. STMicroelectronics NV and its subsidiaries ("ST") reserve the right to make changes, corrections, modifications or improvements, to this document, and the products and services described herein at any time, without notice.

Information in this document is intended as support for authorized communication between ST and Customer only, for internal discussions purposes.

In no event the information disclosed by ST to Customer hereunder can be used against ST, or in a claim brought in front of any Court or Jurisdiction.

At all times you will comply with the following securities rules:

- Do not copy or reproduce all or part of this document
- Keep this document locked away
- Further copies can be provided on a "need to know basis", Please contact your local ST Sales Office or document writer

Information furnished is believed to be accurate and reliable. However, STMicroelectronics assumes no responsibility for the consequences of use of such information nor for any infringement of patents or other rights of third parties which may result from its use. No license is granted by implication or otherwise under any patent or patent rights of STMicroelectronics. Specifications mentioned in this publication are subject to change without notice. This publication supersedes and replaces all information previously supplied. STMicroelectronics products are not authorized for use as critical components in life support devices or systems without express written approval of STMicroelectronics.

The ST logo is a trademark of STMicroelectronics International NV and/or its affiliates, registered in the U.S. and other countries

© 2020 STMicroelectronics International NV and/or its affiliates - All Rights Reserved

[www.st.com](http://www.st.com)

# Thank you

© STMicroelectronics - All rights reserved.

ST logo is a trademark or a registered trademark of STMicroelectronics International NV or its affiliates in the EU and/or other countries.

For additional information about ST trademarks, please refer to [www.st.com/trademarks](http://www.st.com/trademarks).

All other product or service names are the property of their respective owners.



life.augmented