

Table 1: STEVAL-BCNST01V1 bill of materials

Item	Q.ty	Ref.	Part/Value	Description	Manufacturer	Order code
1	1	BATT	Battery Connector	Battery connector	Molex	78171-0002
2	1	CN1	FTSH-105-03-L-D		Samtec	FTSH-105-03-L-D
3	1	CN2	FTSH-104-03-L-D		Samtec	FTSH-104-03-F-D
4	1	CN3	HEADER 4X2	DNM	Any	
5	2	C1,C3	100nF	X7R	Any	
6	2	C2,C4	47µF	Tantal	Any	
7	4	C5,C6,C7,C8	4.7 µF > 6.3 V <2 OHM ESR 3216-16	Tantal	Any	
8	2	C9,C11	100 nF 10 V C_0603	X5R	Any	
9	2	C10,C12	4.7 µF 10 V C_0603	X5R	Any	
10	1	C13	NC C_0603	X7R DNM	Any	
11	2	C14,C15	4.7 µF 10 V C_0603	X5R DNM	Any	
12	1	J1		PHONOJACK STEREO	Switchcraft	35RASMT4BHNTRX
13	4	J5, J6, J7, J8		PCB Hole	Any	
14	1	RESET	SYS_MODE		C&K Components	PTS820 J20M SMTR LFS
15	1	R1	56 K ±1% R_0603		Any	
16	1	R2	140 K ±1% R_0603		Any	
17	9	SB1, SB2, SB3, R3, SB4, R4, SB5, SB6, SB7	0 R R_0603		Any	
18	2	R5, R6	10 K ±1% R_0603		Any	
19	1	SB8	NC R_0603	DNM	Any	
20	1	SWD	CON5		Any	
21	1	TP1	VBAT	DNM	Any	
22	1	TP2	GND	DNM	Any	
23	1	USB	USB-Micro-B	USB-MICRO	GCT	USB3075-30-A
24	1	U1	USBL6-2P6 SOT666	Very low capacitance ESD protection	ST	USBL6-2P6
25	1	U2	PCM1774RGP VQFN20		TI	PCM1774RGP
26	1	U4	LDK120M-R SOT23-5L	Very low noise LDO	ST	<a href="#">LDK120M-R</a>
27	2	U5, U6	VL53L0CXV0DH/1	Time-of-Flight ranging sensor	ST	<a href="#">VL53L0X</a>
28	1	SWD Cable	5 pin 2.54mm - L=15cm	Ribbon cable	Any	

**Table 2: STEVAL-BCNS01V1 bill of materials**

Item	Q.ty	Ref.	Part/Value	Description	Manufacturer	Order code
1	1	A1	JT_2450AT18A100E 3.2x1.6x1.3		Johanson Technology	2450AT18A100E
2	1	A2		U.FL connector DNM	Hirose	U.FL-R-SMT-1(10)
3	1	BATT		Battery Connector	Molex	78171-0002
4	1	CN1	CLP-105-02-L-D		Samtec	CLP-105-02-L-D
5	1	CN2	CLP-104-02-L-D		Samtec	CLP-104-02-L-D
6	3	C1,C6,C34	4.7 µF 6.3 V X5R C_0402	Capacitor	Any	
7	2	C2,C15	10 µF 6.3 V X5R C_0603	Capacitors	Any	
8	6	C3,C10,C17,C25,C27,C	1 µF 10 V X5R C_0402	Capacitors	Any	
9	18	C4,C5,C8,C11,C13,C14, C18,C20,C21,C22,C28, C30,C32,C35,C37,C4	100 nF C_0201 X7R	Capacitors	Any	
10	2	C7,C39	2.2 µF 6.3 V C_0402 X5R	Capacitors	Any	
11	2	C9,C12	10 pF C_0402 C0G	Capacitors	Any	
12	1	C19	220 nF C_0201 X7R	Capacitor	Any	
13	2	C23,C33	12 pF C_0402 C0G	Capacitors	Any	
14	2	C24,C26	100 pF C_0201 C0G	Capacitors	Any	
15	1	C31	150 nF C_0402 X5R	Capacitor	Any	
16	1	C38	NC C_0201 C0G	Capacitor	Any	
17	1	C40	0.5 pF 25 V ±0.1 pF C_0201 C0G	Capacitor	Murata	GJM0335C1ER50BB01D
18	5	LED1,LED2,LED3,LED4,LED5,LE	LED_R LED_0402	LEDs	Any	
19	1	L2	3.9 nH L_0402		Murata	LQG15HN3N9SO2D
20	4	M1,M2,M3,M4	MP34DT06J (3 x 4 x 1 mm)	MEMS digital microphones	ST	<a href="#">MP34DT06JTR</a>
21	2	R1,R22	0 R R_0201	Resistors	Any	
22	4	R2,R4,R18,R19	100 K R_0201	Resistors	Any	
23	1	R3	10 K R_0201	Resistor	Any	
24	8	R5,R6,R9,R10,R11,R12,R	560 R 50 mW R_0201	Resistors	Any	
25	2	R7,R8	4K7 R_0201	Resistors	Any	
26	1	R15	9.1 nH 250 mA R_0201	Resistor	Murata	LQP03TQ9N1H02D
27	1	R16	133 K ±1% R_0201	Resistor	Any	
28	1	R17	56 K ±1% R_0201	Resistor	Any	
29	1	R20	2 K ±1% R_0201	Resistor	Any	
30	1	R21	20 K ±1% R_0201	Resistor	Any	
31	1	R23	10 K ±1% R_0201	Resistor	Any	

Item	Q.ty	Ref.	Part/Value	Description	Manufacturer	Order code
32	1	SW1	SW1	Tactile switch	OMRON ELECTRONIC	B3U-3000P-B
33	1	SW2	SW2	Tactile switch	OMRON ELECTRONIC	B3U-3000P-B
34	1	TP1	VBAT	DNM	Any	
35	1	TP2	GND	DNM	Any	
36	1	TP3	VIn	DNM	Any	
37	1	TP4	SWDIO	DNM	Any	
38	1	TP5	SWDCLK	DNM	Any	
39	1	U1	STM32F446 WLCSP81	Accelerator	ST	STM32F446
40	1	U2	BLUENRG-MSCSP	BLE network processor	ST	<a href="#">BLUENRG-MSCSP</a>
41	1	U3	STBC03J	Battery management	ST	<a href="#">STBC03JR</a>
42	1	U4	AS11P2TLR DFN6L		ST	DFN6L
43	1	U5	BALF-NRG-01D3 Flip-Chip-4	Balun	ST	<a href="#">BALF-NRG-01D3</a>
44	1	U6	LSM303AGR (2 x 2 x 1 mm)	3D accelerometer and magnetometer	ST	<a href="#">LSM303AGR</a>
45	1	U7	LSM6DSM LGA-14 (3x2.5x1 mm)	3D accelerometer and gyroscope	ST	<a href="#">LSM6DSM</a>
46	1	U8	LPS22HB (2 x 2 x 0.76 mm)	MEMS nano pressure sensor	ST	<a href="#">LPS22HB</a>
47	1	X1	16 MHz 2.5x2 mm		NDK	NX2520SA-16.000000MHZ
48	1	X2	32 MHz 2.0x1.6 mm		NDK	NX2016SA 32MHz EXS00A-CS06644

**Table 3: STEVAL-BCNCR01V1 bill of materials**

Item	Q.ty	Ref.	Part/Value	Description	Manufacturer	Order code
1	1	BATT		Battery connector	Molex	78171-0002
2	1	CN1			Samtec	FTSH-105-03-L-DV or FTSH-105-03-F-DV
3	1	CN2			Samtec	FTSH-104-03-L-DV or FTSH-104-03-F-DV
4	2	C1,C4	100 nF X7R C_0402	Capacitor	Any	
5	1	C2	10 µF X5R 10 V C_0603	Capacitor	Any	
6	1	C3	4.7 µF X5R 10 V C_0402	Capacitor	Any	

Item	Q.ty	Ref.	Part/Value	Description	Manufacturer	Order code
7	1	L1	2.2 $\mu$ H 700 mA 20% L_0805 $\pm$ 20%		Wurth Elektronik	74479775222
8	1	R1	120 K 1% R_0402 $\pm$ 1%		Any	
9	1	R2	27 K 1% R_0402 $\pm$ 1%		Any	
10	1	R3	100 K 1% R_0402 $\pm$ 1%		Any	
11	4	R4,R5,R7,R8	47 K R_0402	Resistors	Any	
12	1	R6	NC R_0402	DNM	Any	
13	1	SD		Micro-SD	Molex	503398-1892
14	1	TP1	VBAT	DNM	Any	
15	1	TP2	GND	DNM	Any	
16	1	USB	USB-Micro-B	USB-MICRO	HIROSE	ZX62-B-5PA (33)
17	1	U1	USBLC6-2P6 SOT666	Very low capacitance ESD protection	ST	<a href="#">USBLC6-2P6</a>
18	1	U2	ST1S12XX TSOT23-5L	Step down DC-DC converter	ST	<a href="#">ST1S12XX</a>
19	1	Battery	LiPO-751518 3.7 V 130 mAh	2 pin connector	Himax electronics	LiPO-751518
20	1	Plastic Box	Plastic Box		Any	
21	4	M2-Nut	HEX Nut M2 - steel	M2	RS	
22	2	M2-Screw	12 mm M2 - steel	Pan head - phillips	RS	
23	2	M2-Screw	10 mm M2- steel	Pan head - phillips	RS	

**STMicroelectronics****EVALUATION BOARD LICENSE AGREEMENT**

By using this evaluation board or kit (together with all related software, firmware, components, and documentation provided by ST, "Evaluation Board"), You ("You") are agreeing to be bound by the terms and conditions of this Evaluation Board License Agreement ("Agreement"). Do not use the Evaluation Board until You have read and agreed to this Agreement. Your use of the Evaluation Board constitutes Your acceptance of this Agreement.

**LICENSE**

STMicroelectronics ("ST") grants You the right to use the enclosed Evaluation Board offering limited features only to evaluate and test ST products solely for Your evaluation and testing purposes in a research and development setting. The Evaluation Board shall not be, in any case, directly or indirectly assembled as a part in any production of Yours as it is solely developed to serve evaluation purposes and has no direct function and is not a finished product. If software and/or firmware is accompanied by a separate end user license agreement ("EULA"), then such software and/or firmware shall be governed by such EULA.

**EVALUATION BOARD STATUS**

The Evaluation Board offers limited features allowing You only to evaluate and test the ST products. The Evaluation Board is not intended for consumer or household use. You are not authorized to use the Evaluation Board in any production system, and it may not be offered for sale or lease, or sold, leased or otherwise distributed for commercial purposes. If the Evaluation Board is incorporated in an evaluation system, the evaluation system may be used by You solely for Your evaluation and testing purposes. Such evaluation system may not be offered for sale or lease or sold, leased or otherwise distributed for commercial purposes and must be accompanied by a conspicuous notice as follows: "This device is not, and may not be, offered for sale or lease, or sold or leased or otherwise distributed for commercial purposes".

**OWNERSHIP AND COPYRIGHT**

Title to the Evaluation Board remains with ST and/or its licensors. You may not remove any copyright or other proprietary rights notices without prior written authorization from ST. You may make one copy of the software and/or firmware of the Evaluation Board for back up or archival purposes provided that You reproduce and apply to such copy any copyright or other proprietary rights notices included on or embedded in the software and/or firmware. You agree to prevent any unauthorized copying in whole or in part of the Evaluation Board.

**RESTRICTIONS AND WARNINGS**

Before You handle or use the Evaluation Board, You must carefully review any related documentation provided by ST. Such documentation may contain important warnings. You shall comply with all such warnings and other instructions and employ reasonable safety precautions in using the Evaluation Board. Failure to do so may result in death, personal injury, or property damage. If You have any questions regarding the safe usage of the Evaluation Board, You should contact ST for guidance. You may not sell, assign, sublicense, lease, rent or otherwise distribute the Evaluation Board for commercial purposes, in whole or in part, or use Evaluation Board in a production system, with the exception that if You are an authorized ST distributor, You may resell the Evaluation Board in compliance with the applicable terms and conditions. Except as provided in this Agreement or as explicitly permitted in the documentation of the Evaluation Board, You may not reproduce the Evaluation Board or modify, reverse engineer, de-compile or disassemble its software and/or firmware, in whole or in part. You shall not use the Evaluation Board in any safety critical or functional safety testing, including but not limited to testing of life supporting, military or nuclear applications. ST expressly disclaims any responsibility for such usage which shall be made at Your sole risk, even if ST has been informed in writing of such usage. Unless expressly designated in writing by ST as suitable for use in testing automotive or aerospace applications, You shall not use the Evaluation Board in such testing.

**Notice applicable to Evaluation Boards according to European Regulation**

For the European Regulation of the Evaluation Board, the applicable EU directives are considered, with a particular attention to the Low Voltage Directive (LVD) 2014/35/EU, the Electromagnetic Compatibility (EMC) Directive 2014/30/EU, and the Radio Equipment Directive (RED) 2014/53/EU. If the Evaluation Board is outside the scope of the foregoing Directives, then the General Product Safety Directive (GPSD) 2001/95/EC and Council Directive 93/68/EEC, amending Directive 73/23/EEC on electrical equipment designed for use within certain voltage limits, are applicable.

The Evaluation Board meets the requirements of the Restriction of Hazardous Substances (RoHS 2 or RoHS recast) Directive 2011/65/EU, Annex II, as amended by Directive 2015/863/EU.

**Notice applicable to Evaluation Boards not FCC-Approved**

This kit is designed to allow:

- (1) Product developers to evaluate electronic components, circuitry, or software associated with the kit to determine whether to incorporate such items in a finished product and
- (2) Software developers to write software applications for use with the end product.

This kit is not a finished product and when assembled may not be resold or otherwise marketed unless all required FCC equipment authorizations are first obtained. Operation is subject to the condition that this product not cause harmful interference to licensed radio stations and that this product accept harmful interference. Unless the assembled kit is designed to operate under part 15, part 18 or part 95 of 47 CFR, Chapter I ("FCC Rules"), the operator of the kit must operate under the authority of an FCC license holder or must secure an experimental authorization under part 5 of this chapter.

**For Evaluation Boards annotated as FEDERAL COMMUNICATIONS COMMISSION (FCC) Part 15 Compliant**

- **FCC Interference Statement for Class A Evaluation Boards:** This equipment has been tested and found to comply with the limits for a Class A digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference when the equipment is operated in a commercial environment. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instruction manual, may cause harmful interference to radio communications. Operation of this equipment in a residential area is likely to cause harmful interference in which case the user will be required to correct the interference at his own expense.
- **FCC Interference Statement for Class B Evaluation Boards:** This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:
  - Reorient or relocate the receiving antenna.
  - Increase the separation between the equipment and receiver.
  - Connect the equipment to an outlet on a circuit different from that to which the receiver is connected.
  - Consult the dealer or an experienced radio/TV technician for help.
- This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation. Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

**WARRANTY**

ST WARRANTS THAT IT HAS THE RIGHT TO PROVIDE THE EVALUATION BOARD TO YOU. THIS WARRANTY IS PROVIDED BY ST IN LIEU OF ALL OTHER WARRANTIES, WRITTEN OR ORAL, STATUTORY, EXPRESS OR IMPLIED, INCLUDING ANY WARRANTY AS TO MERCHANTABILITY, NON-INFRINGEMENT, FITNESS FOR ANY PARTICULAR PURPOSE, OR UNINTERRUPTED OR ERROR-FREE OPERATION, ALL OF WHICH ARE EXPRESSLY DISCLAIMED. THE EVALUATION BOARD IS PROVIDED "AS IS".

YOU WARRANT TO ST THAT YOU WILL ENSURE THE EVALUATION BOARD IS USED ONLY BY ELECTRONICS EXPERTS WHO UNDERSTAND THE DANGERS OF HANDLING AND USING SUCH ITEMS, YOU ASSUME ALL RESPONSIBILITY AND LIABILITY FOR ANY IMPROPER OR UNSAFE HANDLING OR USE OF THE EVALUATION BOARD BY YOU, YOUR EMPLOYEES, AFFILIATES, CONTRACTORS, AND DESIGNEES.

**LIMITATION OF LIABILITIES**

IN NO EVENT SHALL ST BE LIABLE TO YOU, WHETHER IN CONTRACT, TORT (INCLUDING NEGLIGENCE), STRICT LIABILITY, OR ANY OTHER LEGAL THEORY, FOR ANY INDIRECT, SPECIAL, CONSEQUENTIAL, INCIDENTAL, PUNITIVE, OR EXEMPLARY DAMAGES WITH RESPECT TO ANY MATTERS RELATING TO THIS AGREEMENT, REGARDLESS OF WHETHER ST HAS BEEN ADVISED OF THE POSSIBILITY OF THE SAME. IN NO EVENT SHALL ST'S LIABILITY ARISING OUT OF THIS AGREEMENT IN THE AGGREGATE EXCEED THE AMOUNT PAID BY YOU UNDER THIS AGREEMENT FOR THE PURCHASE OF THE EVALUATION BOARD, OR TEN UNITED STATES DOLLARS (\$10.00) IF NO PURCHASE PRICE WAS PAID.

**INDEMNIFICATION**

You shall, at Your expense, defend ST and its Affiliates against a claim or action brought by a third party for infringement or misappropriation of any patent, copyright, trade secret or other intellectual property right of a third party to the extent resulting from (1) Your combination of the Evaluation Board with any other component, system, software, or firmware, (2) Your modification of the Evaluation Board, or (3) Your use of the Evaluation Board in a manner not permitted under this Agreement. You shall indemnify ST and its Affiliates against and pay any resulting costs and damages finally awarded against ST or its Affiliates or agreed to in any settlement, provided that You have sole control of the defense and settlement of the claim or action, and ST cooperates in the defense and furnishes all related evidence under its control at Your expense. ST will be entitled to participate in the defense of such claim or action and to employ counsel at its own expense.

"Affiliates" means any corporation or other entity directly or indirectly controlled by, controlling or under common control with the entity in question, for so long as such ownership exists. "Control" means the direct or indirect beneficial ownership of more than fifty (50%) percent of the stock or other equity interests entitled to vote for the election of directors or an equivalent governing body. Any such corporation or other legal entity shall be deemed to be an Affiliate of such Party only as long as such Control exists.

**TERMINATION**

ST may terminate this Agreement without notice if You breach this Agreement. Upon termination, You shall immediately destroy or return all copies of the software, firmware, and documentation of the Evaluation Board to ST and certify in writing to ST that You have done so.

**APPLICABLE LAW AND JURISDICTION**

This Agreement shall be governed, construed and enforced in accordance with the laws of Switzerland, without regard to its conflict of laws rules. The UN Convention on Contracts for the International Sale of Goods shall not apply to this Agreement. In case of dispute and in the absence of an amicable settlement, the only competent jurisdiction shall be the Courts of Geneva, Switzerland. Any breach of this Agreement by You may result in irreparable damage to ST for which ST will not have an

adequate remedy at law. Accordingly, in addition to any other remedies and damages available, You acknowledge and agree that ST may immediately seek enforcement of this Agreement in any jurisdiction by means of specific performance or injunction, without any requirement to post a bond or other security.

#### **SEVERABILITY**

If any provision of this agreement is or becomes, at any time or for any reason, unenforceable or invalid, no other provision of this agreement shall be affected thereby, and the remaining provisions of this agreement shall continue with the same force and effect as if such unenforceable or invalid provisions had not been inserted in this Agreement. In addition, any unenforceable or invalid provision shall be deemed replaced by a provision that is valid and enforceable and that comes closest to expressing the intention of the unenforceable or invalid provision.

#### **WAIVER**

The waiver by either party of any breach of any provision of this Agreement shall not operate or be construed as a waiver of any other or a subsequent breach of the same or a different provision.

#### **RELATIONSHIP OF THE PARTIES**

Nothing in this Agreement shall create, or be deemed to create, any joint venture, partnership, principal-agent, employer-employee or other relationship between the Parties, except that of independent contractors. Neither Party has the authority or power to bind, to contract in the name of, or to create a liability for the other in any way or for any purpose.

#### **SURVIVAL**

Any provision of this Agreement which imposes an obligation after termination of this Agreement shall survive the termination of this Agreement.

#### **SECTION HEADINGS**

Section headings are inserted for convenience only and shall not be used to interpret this Agreement.

#### **WASTE AND RECYCLING**

**The Evaluation Board is not to be disposed of as urban waste. At the end of its life cycle, differentiated waste collection must be followed.** Consult the local authorities for more information on the proper disposal channels. It is mandatory to separately collect the Evaluation Board and make sure it is delivered it to the appropriate waste management and recycling centers.

As of 15 August 2018, in all the countries belonging to the European Union, the Evaluation Board is subject to the WEEE Directive 2012/19/EU requirement; therefore, it is forbidden to dispose of the Evaluation Board as undifferentiated waste or with other domestic wastes. Consult the local authorities for more information on the proper recycling centers.

Disposing of the Evaluation Board incorrectly may cause damage to the environment and may be subject to fines based on specific countries' rules.