Document reference:	Product reference:
January 2026 Vers.2.0	**EVLSTGAP3S3IF Rev. 2.0**
Company: www.st.com	
STMicroelectronics	

All resistors are 1% tolerance unless otherwise indicated
All capacitors are X7R or COG dielectric unless otherwise indicated

Index	Quantity	Reference	Description	Value / Generic Part Number	Voltage	Package	PCB Footprint	Manufacturer	Manufacturer's ordering code / Orderable Part	Supplier	Supplier's ordering code
1	1	C1	THT Electrolitic capacitor	N.M.		Radial p7.5/10 d22	CAPE-R22H50-P100				
2	4	C2,C3,C7,C8	SMT ceramic capacitor	N.M.		Size 2225 (5664 Metric)	C2225				
3	1	C4	Film capacitor	3u3	1.1kV	Pitch 27.5 mm	CAP-RAD-16X31_5H29_5P27_5	Panasonic	ECWFG1B335J or equivalent		
4	10	C5,C9,C21,C23,C35,C37,C39,C41,C44,C45	SMT Ceramic capacitor	1uF	50V	Size 0603 (1608 Metric)	C0603				
5	6	C6,C10,C16,C22,C24,C30	SMT ceramic capacitor	100nF	50V	Size 0603 (1608 Metric)	C0603				
6	6	C11,C12,C15,C25,C26,C29	SMT ceramic capacitor	100pF	16V	Size 0603 (1608 Metric)	C0603				
7	2	C13,C27	SMT ceramic capacitor	N.M.		Size 0603 (1608 Metric)	C0603				
8	2	C14,C28	SMT ceramic capacitor	N.M.	50V	Size 0402 (1005 metric)	C0402				
9	2	C17,C31	SMT ceramic capacitor	47pF	25V	Size 0603 (1608 Metric)	C0603				
10	2	C18,C33	SMT ceramic capacitor	1uF	16V	Size 0603 (1608 Metric)	C0603				
11	2	C19,C32	SMT ceramic capacitor	100nF	16V	Size 0603 (1608 Metric)	C0603				
12	2	C20,C34	SMT ceramic capacitor	N.M.	50V	Size 0603 (1608 Metric)	C0603				
13	4	C36,C40,C42,C46	SMT Ceramic capacitor	4.7uF	50V	Size 1206	C1206				
14	2	C38,C43	SMT Ceramic capacitor	N.M.		Size 0603	C0603				
15	2	C47,C48	SMT ceramic capacitor	10uF	25V	Size 0805 (2012 Metric)	C0805				
16	2	D1,D5	Automotive low drop power Schottky rectifier	STPS2L40ZFY	40V	SOD123Flat	SOD-123	STMicroelectronics	STPS2L40ZFY or equivalent		
17	2	D3,D7	Small signal Schottky diodes	BAT54JFILM	40V	SOD323Flat	SOD-323	STMicroelectronics	BAT54JFILM or equivalent		
18	3	D2,D4,D6	Diode Ultrafast 1200 V, 1 A	STTH112A		SMA	DO-214AC	STMicroelectronics	STTH112A or equivalent		
19	2	D8,D11	SURFACE MOUNT PRECISION ZENER DIODE	BZT585B12T		SOD523	SOD-523	DIODES Incorporated	BZT585B12T or equivalent		
20	2	D9,D12	SURFACE MOUNT PRECISION ZENER DIODE	BZT585B15T		SOD523	SOD-523	Diodes Incorporated	BZT585B15T or equivalent		
21	2	D10,D13	200 mW ZENER DIODE 4.7 V	BZT52C4V7T	4.7V	SOD523	SOD-523	MCC	BZT52C4V7T-TP or equivalent		
22	4	FB1,FB2,FB3,FB4	Ferrite Beads	BLM21AG471SN1		Size 0805	R0805	Murata	BLM21AG471SN1 or Equivalent		
23	3	OUT,HV,GNDPWR	M3 screw **(lasciare fori senza stagno)**	N.M.							
24	3	JR1,R47,R54	SMT Resistor	0		Size 0603	R0603				
25	1	J1	Terminal block T.H. 5 positions, 3.5 mm	MORSV-350-5P_screw		Pitch 3,5 mm	MORS_WR-TBL_691243110005_5P_3V5	Wurth Elektronik	691243110005 or equivalent		
26	1	J2	Strip connector 7 pos, 2.54 mm	STRIP 1x7		1x7 pins	STRIP_7V	Amphenol FCI	68000-407HLF or equivalent		
27	1	J3	Strip connector 6 pos, 2.54 mm	STRIP 1x6		1x6 pins	STRIP_6V	WURTH ELEKTRONIK	61300611121 or equivalent		
28	2	J4,J5	Strip connector 3 pos, 2.54 mm	STRIP 1x3		1x3 pins	STRIP_3V	WURTH ELEKTRONIK	61300311121 or equivalent		
29	4	LED1,LED2,LED3,LED4	WL-SMCW SMT Mono-color Chip LED Waterclear	RED		Size 0805	led-0805	WURTH ELEKTRONIK	150080RS75000 or equivalent		
30	2	Q1,Q2		N.M.		TO-247	TO247-3PIN-SPLIT2				
31	2	Q1A,Q2A	Trench gate field-stop IGBT, M series 650 V, 10 A low-loss	STGP10M65DF2	650V	TO-220	TO220-3PIN-SPLIT2	STMicroelectronics	STGP10M65DF2 or equivalent		
32	2	Q3,Q4	N-channel 60 V, 21 mOhm typ., 7 A STripFET F7, Power MOSFET in a PowerFLAT	N.M.		PowerFLAT 2x2 mm	POWERFLAT6-2X2_P065-E	STMicroelectronics	STL7N6F7 or equivalent		
33	2	Q5,Q6	Low voltage fast-switching NPN power transistors	2STF1360	60V	SOT-89	SOT-89	STMicroelectronics	2STF1360 or Equivalent		
34	2	R1,R2	SMT Resistor	10M		Size 1206 (3216 Metric)	R1206				
35	4	R3,R9,R26,R32	SMT resistor	N.M.		Size 0603 (1608 Metric)	R0603				
36	4	R4,R19,R28,R40	SMT resistor	750		Size 0603 (1608 Metric)	R0603				
37	6	R5,R7,R18,R29,R30,R39	SMT resistor	100		Size 0603 (1608 Metric)	R0603				
38	2	R6,R27	SMT resistor	8.2		Size 1210	R1210				
39	2	R8,R31	SMT resistor	8.2		Size 1210	R1210				
40	2	R10,R33	SMT resistor	N.M.		Size 0805 (2012 Metric)	R0805				
41	11	R11,R14,R17,R20,R21,R22,R38,R41,R48,R55,R58	SMT resistor	N.M.		Size 0402 (1005 metric)	R0402				
42	2	R12,R36	SMT resistor	51K		Size 0603 (1608 Metric)	R0603				
43	2	R13,R34	SMT resistor	10k		Size 0402 (1005 metric)	R0402				
44	2	R16,R37	SMT resistor	1k		Size 0603 (1608 Metric)	R0603				
45	9	R44,R46,R50,R51,R53,R57,R59,R63,R64	SMT resistor	0		Size 0402 (1005 metric)	R0402				
46	1	R23	SMT Resistor	N.M.		Size 1206 (3216 Metric)	R1206				
47	2	R24,R42	SMT resistor	N.M.		Size 0402 (1005 metric)	R0402				
48	2	R25,R43	SMT resistor	N.M.		Size 0402 (1005 metric)	R0402				
49	2	R45,R52	SMT Resistor	1K		Size 0603 (1608 Metric)	R0603				
50	2	R49,R56	SMT Resistor	N.M		Size 0603 (1608 Metric)	R0603				
51	1	R60	SMT resistor	4.7k		Size 0603 (1608 Metric)	R0603				
52	1	R61	SMT resistor	1.47k		Size 0603 (1608 Metric)	R0603				
53	1	R62	SMT resistor	1.18k		Size 0603 (1608 Metric)	R0603				
54	10	TP1,TP2,TP3,TP4,TP5,TP11,TP12,TP13,TP14,TP15	TP for Probe **(lasciare fori senza stagno)**	TP-diam1_27mm-Hole0_8mm		Diam. 1.27, Hole 0.8mm	TP-F0_8_PAD_1_35				
55	9	TP6,TP7,TP8,TP9,TP10,TP16,TP17,TP18,TP19	TP for Probe **(lasciare fori senza stagno)**	TP-diam1_27mm-Hole0_8mm		Diam. 1.27, Hole 0.8mm	TP-1_5				
56	2	U1,U2	Galvanically isolated 3 A single gate driver for IGBT	STGAP3S3IF		SO-16W	SO16_L10_4	STMicroelectronics	STGAP3S3IF		
57	2	U3,U4	5.4kVDC Isolated 2W Gate Drive DC-DC Converters	MGJ2D051515BSC	Vin 5V, Vout1 15V, Vout2 -15V		CONV_MGJ2	Murata	MGJ2D051515BSC or equivalent		
58	1	U5	200 mA low quiescent current and low noise LDO	LDK220M-R		SOT23-5L	SOT23-5L	STMicroelectronics	LDK220M-R or equivalent		
59	1	VP3	PCB Assembly version solder dot **(aggiungere goccia di stagno)**	FULL			square2x2mm				
60	4	VP1,VP2,VP4	PCB Assembly version solder dot **(nessuna goccia di stagno)**	EMPTY			square2x2mm				
61	1	PCB	P.C.B. EVLSTGAP3S3 Rev.2			84x116 mm		STMicroelectronics			
62	4		**Gommini da mettere sotto la board**								