

Table 1: STDES-IDS002V1 bill of materials

Item	Q.ty	Ref.	Part / Value	Description	Manufacturer	Order code
1	1	Transmitter board	-	PV harvester based on SPV1050 and wireless transmission board	ST	STDES-ERH003V1
2	1	Receiver board	-	Wireless receiver board for STDES-IDS003V1 and STDES-IDS002V1 kits	ST	STDES-ERH002V1
3	1	Power monitoring board	-	Power monitoring board for STDES-IDS003V1 and STDES-IDS002V1 kits	ST	STDES-ERH001D

Table 1: STDES-ERH003V1 bill of materials

Item	Q.ty	Ref.	Part / Value	Description	Manufacturer	Order code
1	1	BT1	Li-Ion, 3v6-120 mAh, 2450	Li-Ion Battery	MULTICOMP	LIR2450
2a	1	U13	-	Battery holder	KEYSTONE	3008
2b	0	U13 (DNM, alternate part)	-	Thin Film battery	ST	EFL700A39
3	9	C1,C2,C3,C7, C13,C15,C33, C42,C43	100nF	MLCC Capacitor	MURATA	GCM155R71C104KA55
4	1	C4	22µF	MLCC Capacitor	TDK	C1608X5R0J226M
5	2	C5, C6	6pF	MLCC Capacitors	MULTICOMP	MCCA000087
6	0	C8 (DNM)	-	MLCC Capacitors	-	-
7	2	C9, C20	10µF	MLCC Capacitors	MURATA	GRM188R60J106ME47D
8	5	C10,C14,C34, C35,C37	1µF	MLCC Capacitors	MURATA	GCM188R71E105KA64
9	1	C38, C45 (DNM)	2.2µF	MLCC Capacitors	MURATA	GRM188R61E225KA12D
10	1	C11	100pF	MLCC Capacitors	MURATA	GRM1555C1H101JZ01D
11	3	C12,C16,C28	330pF	MLCC Capacitors	YAGEO	CC0402KRX7R9BB331
12	0	C17, Ctun1 (DNM)	-	MLCC Capacitors	-	-
13	0	C18, C23 (DNM)	-	MLCC Capacitors	-	-
14	1	C19	220pF	MLCC Capacitors	AVX	06035A221JAT2A
15	2	C21, C31	220pF	MLCC Capacitors	MURATA	GRM1555C1H221JA01D
16	1	C22	7pF	MLCC Capacitors	MURATA	GRM1555C1H7R0BA01D
17	1	C24	2.4pF	MLCC Capacitors	MURATA	GRM1555C1H2R4BA01D
18	1	C25	3.6pF	MLCC Capacitors	MURATA	GRM1555C1H3R6CA01D
19	2	C26, C27	18pF	MLCC Capacitors	MULTICOMP	MC0402N180J500CT
20	1	C29	10nF	MLCC Capacitors	MURATA	GCM155R71H103KA55
21	1	C30	1.5pF	MLCC Capacitors	MURATA	GRM1555C1H1R5WA01D
22	1	C32	2pF	MLCC Capacitors	MULTICOMP	MC0402N2R0C500CT
23	1	C36	100nF	MLCC Capacitors	TDK	C1608X7R1H104K080AA
24	2	C39, C40	47µF	MLCC Capacitors	KEMET	C0805C476M9PACTU
25	1	C41	10nF	MLCC Capacitors	MURATA	GRM188R71H103KA01D
26	1	C44	470nF	MLCC Capacitors	MURATA	GRM188R71A474KA61D
27	1	CN1	1A	USB-MICRO-B	TE CONN	1981568-1
28	1	CN2	100 Mils 1 row, 2 ways	2 pins plug	MULTICOMP	MC34745
29	0	Ctun2 (DNM)	-	MLCC Capacitors	-	-
30	1	CX1	2.2µF	MLCC Capacitors	KEMET	C0805C225K4RAC
31	4	D1,D2,D3,D4	0.1A, 100V	Diode	ST	TMMBAT41

Item	Q.ty	Ref.	Part / Value	Description	Manufacturer	Order code
32	0	D6 (DNM)	1A, 20V	Diode	ST	BAT20J
33	1	J1	5pin, 50Ω	Socket for Antenna	RS	526-5785
34	1	J2	1 row, 2 way	2 pins plug	TOPTECK	PH1S25-140GB 6/3-L
35	0	J4 (DNM)	1 row, 3 way	3 pins plug	FCI	95293-101-03LF
36	5	J3, J5, J6, J7, J9	1 row, 3 ways	3 pins plug	FCI	95293-101-03LF
37	1	J8	2 rows, 8 ways	16 pins plug	SAMTEC	SMH-108-02-G-D
38	1	JP1	2 rows, 6 ways	6 pins plug	MOLEX	87758-0616
39	1	L1	10μH	Inductor	MURATA	LQM21FN100M70L
40	1	L2	27nH	Inductor	COILCRAFT	0402CS-27NXGLU
41	1	L3	100nH	Inductor	MURATA	LQG15HSR10J02
42	0	L4 (DNM)	-	Inductor	-	-
43	1	L5	3.6nH	Inductor	MURATA	LQG15HN3N6S02
44	1	L6	5.1nH	Inductor	MURATA	LQG15HN5N1S02
45	1	L7	0Ω	Resistor	YAGEO	RC0402JR-070RL
46	1	L8	18nH	Inductor	MURATA	LQG15HN18NJ02
47	2	L9, L10	15nH	Inductor	MURATA	LQG15HN15NJ02
48	1	L11	4.7μH	Inductor	EPCOS	B82464A4472M
49	1	L12	22μH	Inductor	COILCRAFT	LPS4018-223
50	1	P1	1 row, 8 ways	8 ways connector	MULTICOMP	MC34753
51	13	R1 to R5, R16 to R20 R26 to R28	100Ω	Resistor	YAGEO	RC0402FR-07100RL
52	2	R6, R7	10Ω	Resistor	YAGEO	RC0402FR-0710RL
53	2	R8, R9	100kΩ	Resistor	YAGEO	RC0402FR-07100KL
54	4	R10,R11, R12,R13	10kΩ	Resistor	YAGEO	RC0402FR-0710KL
55	1	R14	560Ω	Resistor	YAGEO	RC0402FR-07560RL
56	1	R15	0Ω	Resistor	YAGEO	RC0402JR-070RL
57	2	R21, R29	750kΩ	Resistor	VISHAY	CRCW0603750KFKEA
58	1	R22	240kΩ	Resistor	VISHAY	CRCW0603240KFKEA
59	1	R23	120kΩ	Resistor	VISHAY	CRCW0603120KFKEA
60	1	R24	100kΩ	Resistor	YAGEO	RC0603FR-07100KL
61	1	R25	422kΩ	Resistor	PANASONIC	ERJ-3EKF4223V
62	2	R31, R32	2MΩ	Resistor	VISHAY	CRCW06032M00FKEA
63	1	R33	5.6MΩ	Resistor	VISHAY	CRCW06035M60FKEA
64	1	R34	1.8MΩ	Resistor	VISHAY	CRCW06031M80FKEA
65	2	R35, R38	3MΩ	Resistor	VISHAY	CRCW06033M00FKEA
66	1	R37	680kΩ	Resistor	TE- CONN	CRG0603F680K
67	1	R36	10MΩ	Resistor	VISHAY	CRCW060310M0FKEA

Item	Q.ty	Ref.	Part / Value	Description	Manufacturer	Order code
68	1	R39	5.36kΩ	Resistor	PANASONIC	ERA-3AEB5361V
69	1	R40	2.05kΩ	Resistor	VISHAY	CRCW06032K05FKEA
70	1	SW1	50mA push button	Push button	OMRON	B3U-1100P-B
71	4	SW2,SW4,SW6,S	5Ω Dual SPDT switch/2:1 Multiplexer	Dual SPDT switch/2:1 Multiplexer	ST	STG3682QTR
72	4	SW3,SW5,SW8,S	0.5Ω Dual SPDT switch	0.5 Ω dual SPDT switch	ST	STG5223QTR
73	2	SW10,SW11	0.5A slide switch	1 row, 3 ways slide switch	WURTH	450302014072
74	3	TP1, TP3, TP17	BLACK	TEST POINT	KEYSTONE	5001
75	2	TP2, TP4	RED	TEST POINT	KEYSTONE	5000
76	0	TP5 to TP16, TP18 (DNM)	TEST POINT	TEST POINT	-	-
77	1	U1	MCU	STM32 MCU	ST	STM32L151CBT6
78	1	U2	12 bits, 0.0625°C resolution	T-SENSOR	ST	STTS751-ODP3F
79	1	U3	±2g to ±16g Accelerometer	MEMS	ST	LIS3DHTR
80	1	U4	260-1260 hPa Pressure sensor	MEMS	ST	LPS25HTR
81	1	U5	Sub 1GHz transceiver	Wireless Transceiver	ST	SPIRIT1QTR
82	1	U6	8192 × 8 bits (I2C mode)	E2PROM	ST	M24LR64E-RDW6T/2
83	1	U7	50mA voltage regulator	Voltage regulator	ST	STLQ50C-R
84	1	U9	85mA voltage regulator	Voltage regulator	ST	ST715MR
85	1	U10	150mA voltage regulator	Voltage regulator	ST	STLQ015M25R
86	1	U11	Harvester and battery charger	Harvester and battery charger	ST	SPV1050TTR
87	2	U12, U15	5V PV PANEL	PV-PANEL	PANSONIC	AM-1801CA
88	1	X1	4MHz Oscillator	Crystal Oscillator	MURATA	CSTCR4M00G53Z-R0
89	1	X2	32MHz Crystal Oscillator	Crystal Oscillator	ABRACON CORPORATIO	ABS07-32.768KHZ-6-T
90	1	XTAL1	50MHz Crystal	Crystal Oscillator	TXC	7M-50.000MAAJ-T
91	1	U14	Ambient Light Sensor	Ambient Light Sensor	OSRAM	SFH 5711
92	1	R42	82kΩ	Resistor	ROHM	MCR03EZPFX8202

Item	Q.ty	Ref.	Part / Value	Description	Manufacturer	Order code
93	1	-	USB Cable (A, micro USB B)	USB Cable (A, micro USB B)	-	-
94	1	J_1	868MHz to 915MHz SMA ANTENNA	ANTENNA	LPRS	WR868

Table 1: STDES-ERH002V1 bill of materials

Item	Q.ty	Ref.	Part / Value	Description	Manufacturer	Order code
1	5	C1, C2, C3, C15, C17	100nF	Capacitor	MURATA	GCM155R71C104KA55
2	1	C4	22μF	Capacitor	TDK	C1608X5R0J226M
3	2	C5, C6	6pF	Capacitor	MULTICOMP	MCCA000087
4	1	C7	100nF	Capacitor	KEMET	C0603C104K5RACTU
5	0	C8, C11 (DNM)	-	Capacitor	-	-
6	3	C9, C12, C16	1μF	Capacitor	MURATA	GCM188R71E105KA64
7	1	C10	4.7μF	Capacitor	YAGEO	CC0603KRX5R5BB475
8	1	C13	100pF	Capacitor	MURATA	GRM1555C1H101JZ01D
9	3	C14, C18, C26	330pF	Capacitor	YAGEO	CC0402KRX7R9BB331
10	0	C19, Ctun1 (DNM)	-	Capacitor	-	-
11	2	C20, C29	220pF	Capacitor	MURATA	GRM1555C1H221JA01D
12	1	C21	7pF	Capacitor	MURATA	GJM1555C1H7R0BB01D
13	1	C22	2.4pF	Capacitor	MURATA	GRM1555C1H2R4WA01D
14	1	C23	3.6pF	Capacitor	MURATA	GRM1555C1H3R6CA01D
15	2	C24, C25	18pF	Capacitor	MULTICOMP	MC0402N180J500CT
16	1	C27	10nF	Capacitor	MURATA	GCM155R71H103KA55
17	1	C28	1.5pF	Capacitor	MURATA	GRM1555C1H1R5WA01D
18	1	C30	2pF	Capacitor	MULTICOMP	MC0402N2R0C500CT
19	1	J1	5pin, 50Ω	Socket for Antenna	RS	526-5785
20	1	J2	1 row, 2 way	2 pins plug	TOPTECK	PH1S25-140GB 6/3-L
21	1	L1	10μH	Inductor	MURATA	LQM21FN100M70L
22	1	L2	27nH	Inductor	COILCRAFT	0402CS-27NXGLU
23	1	L3	100nH	Inductor	MURATA	LQG15HSR10J02
24	0	L4 (DNM)	-	Inductor	-	-
25	1	L5	3.6nH	Inductor	MURATA	LQG15HN3N6S02
26	1	L6	5.1nH	Inductor	MURATA	LQG15HN5N1S02
27	1	L7	0Ω	Resistor	YAGEO	RC0402JR-070RL
28	1	L8	18nH	Inductor	MURATA	LQG15HN18NJ02
29	2	L9, L10	15nH	Inductor	MURATA	LQG15HN15NJ02
30	1	P1	2 rows, 20 ways	JTAG	TE CONN	2-1634689-0
31	1	P2	Socket USB-B	Socket USB-B	TE CONN	292304-1
32	2	R2, R3	10Ω	Resistor	TE CONN	CRG0402F10R
33	1	R4	1MΩ	Resistor	YAGEO	RC0402FR-071ML
34	4	R5, R6, R7, R8	10kΩ	Resistor	YAGEO	RC0402FR-0710KL
35	1	R9	560Ω	Resistor	YAGEO	RC0402FR-07560RL
36	1	R10	0Ω	Resistor	YAGEO	RC0402JR-070RL
37	0	R11 (DNM)	-	Resistor	-	-
38	1	R12	9.76kΩ	Resistor	VISHAY	CRCW06039K76FKEA

Item	Q.ty	Ref.	Part / Value	Description	Manufacturer	Order code
39	1	R13	5.6kΩ	Resistor	TE CONN	CRGH0603J5K6
40	1	R14	0.01Ω	Resistor	YAGEO	PF0603FRE7T0R01Z
41	1	SW1	PUSH BUTTON	RESET BUTTON	DIPTRONICS	DTSM-61NVT-R
42	2	TP1, TP3	RED Test Point	Test Point	KEYSTONE	5000
43	2	TP2, TP4	BLACK Test Point	Test Point	KEYSTONE	5001
44	1	U1	32MHz MCU	MCU	ST	STM32L151CBT6
45	1	U2	85mA LDO	Voltage Regulator	ST	ST715MR
46	1	U3	Sub 1GHz transceiver	Wireless Transceiver	ST	SPIRIT1QTR
47	1	X1	4MHz Oscillator	Crystal Oscillator	MURATA	CSTCR4M00G53Z-R0
48	1	X2	32MHz Crystal Oscillator	Crystal Oscillator	ABRACON CORPORATION	ABS07-32.768KHZ-6-T
49	1	XTAL1	50MHz Crystal	Crystal Oscillator	TXC	7M-50.000MAAJ-T
50	1	-	868MHz to 915MHz SMA ANTENNA	ANTENNA	LPRS	WR868
51	1	-	USB TYPE A USB TYPE B	USB CABLE	RS	815-8466

Table 1: STDES-ERH001D bill of materials

Item	Q.ty	Ref.	Part / Value	Description	Manufacturer	Order code
1	1	C1	4.7 μ F	Capacitor	MURATA	GCM21BR71C475KA73L
2	1	C2	100 nF	Capacitor	AVX	08053C104KAT2A
3	5	C3, C4, C7, C11, C24	10 μ F	Capacitor	MURATA	GRM188R61E106MA73D
4	2	C5, C9	220 pF	Capacitor	MURATA	GRM155R71H221KA01D
5	0	C6, C10 (DNM)	-	Capacitor	-	-
6	17	C12 to C15 C18 to C23 C25 to C31	100 nF	Capacitor	KEMET	C0603C104K4RAC
7	1	C16	10 nF	Capacitor	MURATA	GRM188R71C103KA01D
8	1	C17	1 nF	Capacitor	KEMET	C0603C102J5GACTU
9	1	CN1	USB TYPE B	USB-B socket	MOLEX	67068-8010
10	1	P8	2 rows, 16 ways	Connector	FCI	68021-116HLF
11	1	D1	0.1 A, 100 V	Diode	ST	TMMBAT41
12	1	J2	1 row, 2 ways	Jumper	MOLEX	22-28-4023
13	1	L1	10 μ H	Inductor	MURATA	LQH43CN100K03L
14	1	P2	2 rows, 20 ways	JTAG connector	ASSMANN	AWHW 20A-0202-T
15	2	R1, R2	10 Ω	Resistor	BOURNS	CR0603-JW-100GLF
16	1	R3	1.5 k Ω	Resistor	YAGEO	232270265152
17	1	R4	0.1 Ω	Resistor	BOURNS	CRL0603-FW-R100ELF
18	1	R5	390 Ω	Resistor	YAGEO	232270265311
19	1	R7	909 k Ω	Resistor	VISHAY	CRCW0603909KFKEA
20	5	R8, R12, R27, R28, R29	100 k Ω	Resistor	BOURNS	CR0603-FX-1003ELF
21	3	R9, R23, R32	2 k Ω	Resistor	PANASONIC	ERJ3RBD2001V
22	1	R10	57.6 k Ω	Resistor	PANASONIC	ERA3AEB5762V
23	1	R11	33 k Ω	Resistor	PANASONIC	ERJ3RBD3302V
24	1	R13	31.6 k Ω	Resistor	VISHAY	CRCW060331K6FKEA
25	6	R14, R15, R16, R17, R18, R20	10 k Ω	Resistor	YAGEO	232270265103
26	2	R19, R26	560 Ω	Resistor	TE CONN	CRG0603F560R
27	3	R21, R30, R35	2.49 Ω	Resistor	TE CONN	CPF0603F2R49C1
28	3	R22, R31, R36	37.4 Ω	Resistor	VISHAY	CRCW060337R4FKEA
29	1	R24, R33, R38	12 k Ω	Resistor	TE CONN	CRG0603F12K
30	3	R25, R34, R39	510 Ω	Resistor	PANASONIC	ERJ3RBD5100V
31	1	R37	20 k Ω	Resistor	VISHAY	CRCW060320K0FKEA
32	1	SW1	SPST push button	PUSH BUTTON	TE CONN	4-1437565-1
33	1	SW2	0.4 A, 60 V	Opto-coupler	OMRON	G3VM-61H1
34	1	U1	1.4MHz DC/DC	Step-up Converter	LT	LT1618EDD

Item	Q.ty	Ref.	Part / Value	Description	Manufacturer	Order code
35	2	U2, U3	85 mA LDO	Voltage Regulator	ST	ST715MR
36	1	U4	72 MHz MCU	Micro Controller	ST	STM32F103CBT6
37	1	U5	6 channels 24 bits	ADC converter	Microchip	MCP3903-I/SS
38	3	U6, U10, U13	-0.1 V to 28 V	Current Sense Amplifier	Maxim Integrated	MAX9928FAUA+
39	3	U7, U9, U12	2 Channels Analog Switch	Analog Switch	ANALOG DEVICES	ADG1636BRUZ
40	1	X1	8 MHz	Crystal Oscillator	MURATA	CSTCE8M00G52-R0
41	1	X2	4 MHz	Crystal Oscillator	MURATA	CSTCR4M00G53-R0
42	1	-	TYPE B TYPE A	USB Cable	RS	815-8466
43	3	U8, U11, U14	126 dB	Operational amplifier	TI	OPA140AIDGKT

STMicroelectronics**EVALUATION BOARD LICENSE AGREEMENT**

By using this evaluation board or kit (together with all related software, firmware, components, and documentation provided by ST, "Evaluation Board"), You ("You") are agreeing to be bound by the terms and conditions of this Evaluation Board License Agreement ("Agreement"). Do not use the Evaluation Board until You have read and agreed to this Agreement. Your use of the Evaluation Board constitutes Your acceptance of this Agreement.

LICENSE

STMicroelectronics ("ST") grants You the right to use the enclosed Evaluation Board offering limited features only to evaluate and test ST products solely for Your evaluation and testing purposes in a research and development setting. The Evaluation Board shall not be, in any case, directly or indirectly assembled as a part in any production of Yours as it is solely developed to serve evaluation purposes and has no direct function and is not a finished product. If software and/or firmware is accompanied by a separate end user license agreement ("EULA"), then such software and/or firmware shall be governed by such EULA.

EVALUATION BOARD STATUS

The Evaluation Board offers limited features allowing You only to evaluate and test the ST products. The Evaluation Board is not intended for consumer or household use. You are not authorized to use the Evaluation Board in any production system, and it may not be offered for sale or lease, or sold, leased or otherwise distributed for commercial purposes. If the Evaluation Board is incorporated in an evaluation system, the evaluation system may be used by You solely for Your evaluation and testing purposes. Such evaluation system may not be offered for sale or lease or sold, leased or otherwise distributed for commercial purposes and must be accompanied by a conspicuous notice as follows: "This device is not, and may not be, offered for sale or lease, or sold or leased or otherwise distributed for commercial purposes".

OWNERSHIP AND COPYRIGHT

Title to the Evaluation Board remains with ST and/or its licensors. You may not remove any copyright or other proprietary rights notices without prior written authorization from ST. You may make one copy of the software and/or firmware of the Evaluation Board for back up or archival purposes provided that You reproduce and apply to such copy any copyright or other proprietary rights notices included on or embedded in the software and/or firmware. You agree to prevent any unauthorized copying in whole or in part of the Evaluation Board.

RESTRICTIONS AND WARNINGS

Before You handle or use the Evaluation Board, You must carefully review any related documentation provided by ST. Such documentation may contain important warnings. You shall comply with all such warnings and other instructions and employ reasonable safety precautions in using the Evaluation Board. Failure to do so may result in death, personal injury, or property damage. If You have any questions regarding the safe usage of the Evaluation Board, You should contact ST for guidance. You may not sell, assign, sublicense, lease, rent or otherwise distribute the Evaluation Board for commercial purposes, in whole or in part, or use Evaluation Board in a production system, with the exception that if You are an authorized ST distributor, You may resell the Evaluation Board in compliance with the applicable terms and conditions. Except as provided in this Agreement or as explicitly permitted in the documentation of the Evaluation Board, You may not reproduce the Evaluation Board or modify, reverse engineer, de-compile or disassemble its software and/or firmware, in whole or in part. You shall not use the Evaluation Board in any safety critical or functional safety testing, including but not limited to testing of life supporting, military or nuclear applications. ST expressly disclaims any responsibility for such usage which shall be made at Your sole risk, even if ST has been informed in writing of such usage. Unless expressly designated in writing by ST as suitable for use in testing automotive or aerospace applications, You shall not use the Evaluation Board in such testing.

Notice applicable to Evaluation Boards according to European Regulation

For the European Regulation of the Evaluation Board, the applicable EU directives are considered, with a particular attention to the Low Voltage Directive (LVD) 2014/35/EU, the Electromagnetic Compatibility (EMC) Directive 2014/30/EU, and the Radio Equipment Directive (RED) 2014/53/EU. If the Evaluation Board is outside the scope of the foregoing Directives, then the General Product Safety Directive (GPSD) 2001/95/EC and Council Directive 93/68/EEC, amending Directive 73/23/EEC on electrical equipment designed for use within certain voltage limits, are applicable.

The Evaluation Board meets the requirements of the Restriction of Hazardous Substances (RoHS 2 or RoHS recast) Directive 2011/65/EU, Annex II, as amended by Directive 2015/863/EU.

Notice applicable to Evaluation Boards not FCC-Approved

This kit is designed to allow:

- (1) Product developers to evaluate electronic components, circuitry, or software associated with the kit to determine whether to incorporate such items in a finished product and
- (2) Software developers to write software applications for use with the end product.

This kit is not a finished product and when assembled may not be resold or otherwise marketed unless all required FCC equipment authorizations are first obtained. Operation is subject to the condition that this product not cause harmful interference to licensed radio stations and that this product accept harmful interference. Unless the assembled kit is designed to operate under part 15, part 18 or part 95 of 47 CFR, Chapter I ("FCC Rules"), the operator of the kit must operate under the authority of an FCC license holder or must secure an experimental authorization under part 5 of this chapter.

For Evaluation Boards annotated as FEDERAL COMMUNICATIONS COMMISSION (FCC) Part 15 Compliant

- **FCC Interference Statement for Class A Evaluation Boards:** This equipment has been tested and found to comply with the limits for a Class A digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference when the equipment is operated in a commercial environment. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instruction manual, may cause harmful interference to radio communications. Operation of this equipment in a residential area is likely to cause harmful interference in which case the user will be required to correct the interference at his own expense.
- **FCC Interference Statement for Class B Evaluation Boards:** This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:
 - Reorient or relocate the receiving antenna.
 - Increase the separation between the equipment and receiver.
 - Connect the equipment to an outlet on a circuit different from that to which the receiver is connected.
 - Consult the dealer or an experienced radio/TV technician for help.
- This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation. Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

WARRANTY

ST WARRANTS THAT IT HAS THE RIGHT TO PROVIDE THE EVALUATION BOARD TO YOU. THIS WARRANTY IS PROVIDED BY ST IN LIEU OF ALL OTHER WARRANTIES, WRITTEN OR ORAL, STATUTORY, EXPRESS OR IMPLIED, INCLUDING ANY WARRANTY AS TO MERCHANTABILITY, NON-INFRINGEMENT, FITNESS FOR ANY PARTICULAR PURPOSE, OR UNINTERRUPTED OR ERROR-FREE OPERATION, ALL OF WHICH ARE EXPRESSLY DISCLAIMED. THE EVALUATION BOARD IS PROVIDED "AS IS".

YOU WARRANT TO ST THAT YOU WILL ENSURE THE EVALUATION BOARD IS USED ONLY BY ELECTRONICS EXPERTS WHO UNDERSTAND THE DANGERS OF HANDLING AND USING SUCH ITEMS, YOU ASSUME ALL RESPONSIBILITY AND LIABILITY FOR ANY IMPROPER OR UNSAFE HANDLING OR USE OF THE EVALUATION BOARD BY YOU, YOUR EMPLOYEES, AFFILIATES, CONTRACTORS, AND DESIGNEES.

LIMITATION OF LIABILITIES

IN NO EVENT SHALL ST BE LIABLE TO YOU, WHETHER IN CONTRACT, TORT (INCLUDING NEGLIGENCE), STRICT LIABILITY, OR ANY OTHER LEGAL THEORY, FOR ANY INDIRECT, SPECIAL, CONSEQUENTIAL, INCIDENTAL, PUNITIVE, OR EXEMPLARY DAMAGES WITH RESPECT TO ANY MATTERS RELATING TO THIS AGREEMENT, REGARDLESS OF WHETHER ST HAS BEEN ADVISED OF THE POSSIBILITY OF THE SAME. IN NO EVENT SHALL ST'S LIABILITY ARISING OUT OF THIS AGREEMENT IN THE AGGREGATE EXCEED THE AMOUNT PAID BY YOU UNDER THIS AGREEMENT FOR THE PURCHASE OF THE EVALUATION BOARD, OR TEN UNITED STATES DOLLARS (\$10.00) IF NO PURCHASE PRICE WAS PAID.

INDEMNIFICATION

You shall, at Your expense, defend ST and its Affiliates against a claim or action brought by a third party for infringement or misappropriation of any patent, copyright, trade secret or other intellectual property right of a third party to the extent resulting from (1) Your combination of the Evaluation Board with any other component, system, software, or firmware, (2) Your modification of the Evaluation Board, or (3) Your use of the Evaluation Board in a manner not permitted under this Agreement. You shall indemnify ST and its Affiliates against and pay any resulting costs and damages finally awarded against ST or its Affiliates or agreed to in any settlement, provided that You have sole control of the defense and settlement of the claim or action, and ST cooperates in the defense and furnishes all related evidence under its control at Your expense. ST will be entitled to participate in the defense of such claim or action and to employ counsel at its own expense.

"Affiliates" means any corporation or other entity directly or indirectly controlled by, controlling or under common control with the entity in question, for so long as such ownership exists. "Control" means the direct or indirect beneficial ownership of more than fifty (50%) percent of the stock or other equity interests entitled to vote for the election of directors or an equivalent governing body. Any such corporation or other legal entity shall be deemed to be an Affiliate of such Party only as long as such Control exists.

TERMINATION

ST may terminate this Agreement without notice if You breach this Agreement. Upon termination, You shall immediately destroy or return all copies of the software, firmware, and documentation of the Evaluation Board to ST and certify in writing to ST that You have done so.

APPLICABLE LAW AND JURISDICTION

This Agreement shall be governed, construed and enforced in accordance with the laws of Switzerland, without regard to its conflict of laws rules. The UN Convention on Contracts for the International Sale of Goods shall not apply to this Agreement. In case of dispute and in the absence of an amicable settlement, the only competent jurisdiction shall be the Courts of Geneva, Switzerland. Any breach of this Agreement by You may result in irreparable damage to ST for which ST will not have an

adequate remedy at law. Accordingly, in addition to any other remedies and damages available, You acknowledge and agree that ST may immediately seek enforcement of this Agreement in any jurisdiction by means of specific performance or injunction, without any requirement to post a bond or other security.

SEVERABILITY

If any provision of this agreement is or becomes, at any time or for any reason, unenforceable or invalid, no other provision of this agreement shall be affected thereby, and the remaining provisions of this agreement shall continue with the same force and effect as if such unenforceable or invalid provisions had not been inserted in this Agreement. In addition, any unenforceable or invalid provision shall be deemed replaced by a provision that is valid and enforceable and that comes closest to expressing the intention of the unenforceable or invalid provision.

WAIVER

The waiver by either party of any breach of any provision of this Agreement shall not operate or be construed as a waiver of any other or a subsequent breach of the same or a different provision.

RELATIONSHIP OF THE PARTIES

Nothing in this Agreement shall create, or be deemed to create, any joint venture, partnership, principal-agent, employer-employee or other relationship between the Parties, except that of independent contractors. Neither Party has the authority or power to bind, to contract in the name of, or to create a liability for the other in any way or for any purpose.

SURVIVAL

Any provision of this Agreement which imposes an obligation after termination of this Agreement shall survive the termination of this Agreement.

SECTION HEADINGS

Section headings are inserted for convenience only and shall not be used to interpret this Agreement.

WASTE AND RECYCLING

The Evaluation Board is not to be disposed of as urban waste. At the end of its life cycle, differentiated waste collection must be followed. Consult the local authorities for more information on the proper disposal channels. It is mandatory to separately collect the Evaluation Board and make sure it is delivered to the appropriate waste management and recycling centers.

As of 15 August 2018, in all the countries belonging to the European Union, the Evaluation Board is subject to the WEEE Directive 2012/19/EU requirement; therefore, it is forbidden to dispose of the Evaluation Board as undifferentiated waste or with other domestic wastes. Consult the local authorities for more information on the proper recycling centers.

Disposing of the Evaluation Board incorrectly may cause damage to the environment and may be subject to fines based on specific countries' rules.