

## Power management evaluation board based on the stepdown regulators L6981, L7983, ST1PS03, and the ST730 LDO



### Features

- L6981
  - 3.5 V to 38 V operating input voltage
  - Output voltage from 0.85 V to VIN
  - 1.5 A DC output current
  - Internal compensation network
  - 2  $\mu$ A shutdown current
  - Internal soft-start
  - Enable function
  - Overvoltage protection
  - Thermal protection
- L7983
  - 3.5 V to 60 V operating input voltage
  - Output voltage from 0.85 V to VIN
  - 300 mA DC output current
  - Internal compensation network
  - 2.3  $\mu$ A shutdown current
  - Internal soft-start
  - Enable function
  - Overvoltage protection
- ST1PS03
  - 1.8 V to 5.5 V operating input voltage
  - Output voltage selectable from 1.6 V to 3.3 V
  - 400 mA DC output current
  - 500 nA (typ.) quiescent current
  - Load switch controlled by AUX input
  - Enable function
- ST730
  - 2.5 V to 28 V input voltage range
  - Output voltage from 1.2 V to VIN
  - 300 mA DC output current
  - 5  $\mu$ A (typ) no-load quiescent current
  - Current limit and SOA protection
  - Enable function

### Product summary

Power management evaluation board based on the stepdown regulators L7983, L6981, ST1PS03, and the ST730 LDO	STEVAL-QUADV01
38 V, 1.5 A synchronous step-down converter with low quiescent current	L6981CDR
60 V 300 mA synchronous step-down switching regulator with 10 $\mu$ A quiescent current	L7983PUR
400 mA nano-quiescent synchronous step-down converter with digital voltage selection, Power Good and independent Load Switch	ST1PS03AQTR
300 mA, 28 V low-dropout voltage regulator, with 5 $\mu$ A quiescent current	ST730MR

### Description

The STEVAL-QUADV01 evaluation board is based on the L6981 (capable of delivering up to 1.5 A DC), the L7983 (capable of delivering up to 300 mA DC), the ST1PS03 (capable of delivering up to 400 mA DC) synchronous monolithic step-down regulators, and the ST730 (capable of delivering up to 300 mA DC) LDO regulator.

The combination of input voltage and output current ranges, and other embedded features makes the evaluation tool suitable for a broad range of applications.

**Product summary**

Applications	DC-DC Converters, Linear Voltage Regulators
--------------	--

# 1 Schematic diagrams

Figure 1. STEVAL-QUADV01 circuit schematic (1 of 4)







Figure 2. STEVAL-QUADV01 circuit schematic (2 of 4)





**Figure 4. STEVAL-QUADV01 circuit schematic (4 of 4)**



## Revision history

**Table 1. Document revision history**

Date	Version	Changes
17-Apr-2023	1	Initial release.

**IMPORTANT NOTICE – READ CAREFULLY**

STMicroelectronics NV and its subsidiaries (“ST”) reserve the right to make changes, corrections, enhancements, modifications, and improvements to ST products and/or to this document at any time without notice. Purchasers should obtain the latest relevant information on ST products before placing orders. ST products are sold pursuant to ST’s terms and conditions of sale in place at the time of order acknowledgment.

Purchasers are solely responsible for the choice, selection, and use of ST products and ST assumes no liability for application assistance or the design of purchasers’ products.

No license, express or implied, to any intellectual property right is granted by ST herein.

Resale of ST products with provisions different from the information set forth herein shall void any warranty granted by ST for such product.

ST and the ST logo are trademarks of ST. For additional information about ST trademarks, refer to [www.st.com/trademarks](http://www.st.com/trademarks). All other product or service names are the property of their respective owners.

Information in this document supersedes and replaces information previously supplied in any prior versions of this document.

© 2023 STMicroelectronics – All rights reserved