

User manual

Getting started with X-NUCLEO-53L5A1 Time-of-Flight 8x8 multi-zone ranging sensor with wide FoV based on the VL53L5CX for STM32 Nucleo

Introduction

This document provides detailed hardware information on the X-NUCLEO-53L5A1 expansion board. This expansion board is compatible with the STM32 Nucleo family and the Arduino™ electronic boards. It is designed around the VL53L5CX multi-zone ranging sensor and is based on the ST patented FlightSense technology.

To allow the user to validate the VL53L5CX in an environment as close as possible to its final application, the X-NUCLEO-53L5A1 expansion board is delivered with a holder in which three different height spacers of 0.25 mm, 0.5 mm, and 1 mm can be fitted with the cover glass above the spacer. The height spacers are used to simulate different air gap distances between the VL53L5CX sensor and the cover glass.



Figure 1. X-NUCLEO-53L5A1 expansion board, spacers, and cover glass



UM2889 - Rev 1 page 2/12



1 Overview

The X-NUCLEO-53L5A1 expansion board features the VL53L5CX multi-zone ranging sensor, based on ST's FlightSense, Time-of-Flight (ToF) technology.

It is compatible with the STM32 Nucleo development board family, and with the Arduino UNO R3 connector layout.

Several ST expansion boards can be stacked through the Arduino connectors, which allows, for example, the development of VL53L5CX applications with Bluetooth or Wi-Fi interfaces.

The X-NUCLEO-53L5A1 expansion board is delivered with:

- Three spacers of 0.25 mm, 0.5 mm, and 1 mm height, used to simulate different air gaps between the VL53L5CX and the cover glass.
- A cover glass to simulate the integration of the VL53L5CX into the customer's final product.
- Two 9-pin connectors to enable the customer to connect the two breakout boards onto the X-NUCLEO-53L5A1 expansion board.

Note:

The VL53L5CX is delivered with a liner to prevent potential foreign material from penetrating inside the module holes during the assembly process. This liner must be removed at the latest possible step during final assembly, before module calibration.

Table 1. Ordering information

Order code	Description
X-NUCLEO-53L5A1	STM32 Nucleo expansion board - spacers and glass

UM2889 - Rev 1 page 3/12



2 Document references

Table 2. Document references

Description	DocID
VL53L5CX datasheet	DS13754
X-NUCLEO-53L5A1 data brief	DB4505
P-NUCLEO-53L5A1 data brief	DB4509
X-CUBE-TOF1 data brief	DB4449
VL53L5CX-SATEL data brief	DB4506

UM2889 - Rev 1 page 4/12



3 X-NUCLEO-53L5A1 expansion board

This section describes the X-NUCLEO-53L5A1 expansion board features and provides useful information for understanding the electrical characteristics.

ARDUINO HEARDERS NUCLEO-F401RE ARDUINO / F401RE CN5 D15 / PB8 10 D14 / PB9 9 SDA 8 GND 7 D13 / PA5 6 D12 / PA6 5 D11 / PA7 4 D10 / PB6 3 D9 / PC7 2 INT_L D8 / PA9 1 I2C_RST_R D7 / PA8 8 I2C_RST_L D6 / PB10_7 SDA INT_C D5 / PB4 6 LPn_C U2 SCL I2C_RST_C D4 / PB5 _5 LPn_R +3V3 VL53L5CX D3 / PB3 4 LPn_C INT_R D2 / PA10 3 GND D1 / PA2 2 D0 / PA3 1 J5_Right Satellite CN6 Right header GND 3 +3V3 _4 J5_Left Satellite GND 6 Left header GND 7 GND PWR_EN_L A0 / PA0 _1 U1 A1 / PA1 _2 +3V3 Voltage Regulator PWR_EN_C A4 / PC1 _5 PWR_EN_R A5 / PC0 6

Figure 2. X-NUCLEO-53L5A1 expansion board schematic diagram

UM2889 - Rev 1 page 5/12



3.1 Description

The board allows the user to test the VL53L5CX functionality, to program it and to understand how to develop an application using the VL53L5CX. It integrates:

- 3.3 V regulator to supply the VL53L5CX
- · Level translators to adapt the I/O level to the main board of the microcontroller
- Arduino UNO R3 connectors
- Optional VL53L5CX breakout board connectors
- · Solder drops to allow different configurations of the expansion board

It is fundamental to program a microcontroller to control the VL53L5CX through the I2C bus. The application software and an example of the C-ANSI source code are available on www.st.com.

The X-NUCLEO-53L5A1 expansion board and STM32 Nucleo development board are connected through the Arduino UNO R3 connectors CN5, CN6, CN8, and CN9 as shown in Figure 2. X-NUCLEO-53L5A1 expansion board schematic diagram.

The X-NUCLEO-53L5A1 must be plugged onto the STM32 Nucleo development board through the Arduino UNO R3 connectors.

3.2 Electrical schematic

The electrical schematics can be downloaded at www.st.com, in the "CAD Resources" section of the X-NUCLEO-53L5A1.

3.3 List of materials

The list of material can be downloaded at www.st.com, in the "CAD Resources" section of the X-NUCLEO-53L5A1.

UM2889 - Rev 1 page 6/12




4 VL53L5CX breakout board

The VL53L5CX breakout boards are not present in the X-NUCLEO-53L5A1 package. They can be purchased by pack of two PCB under the reference VL53L5CX-SATEL.

The VL53L5CX breakout boards are supplied at 3.3 V by the regulator present on the X-NUCLEO-53L5A1 expansion board.

For 3.3 V supply applications, the breakout boards can be broken along the red line as shown in the figure below, to use the "mini PCB". This set up is easier to integrate into a customer device due to its small size.






The VL53L5CX breakout boards can be directly plugged onto the VL53L5CX expansion board through two 9-pin connectors, or they can be connected to the board through flying wires (see figure below).

UM2889 - Rev 1 page 7/12



Figure 4. VL53L5CX mini PCB flying wire connection to X-NUCLEO-53L5A1 expansion board





UM2889 - Rev 1 page 8/12



5 Safety considerations

5.1 Electrostatic precaution

The user should exercise electrostatic precautions, including using ground straps when using the X-NUCLEO-53L5A1 expansion board. Failure to prevent electrostatic discharge could damage the device.

Figure 6. Electrostatic logo



5.2 Laser safety considerations

The VL53L5CX contains a laser emitter and corresponding drive circuitry. The laser output is designed to remain within Class 1 laser safety limits under all reasonably foreseeable conditions including single faults, in compliance with the IEC 60825-1:2014 (third edition). The laser output remains within Class 1 limits as long as STMicroelectronic's recommended device settings are used and the operating conditions specified in the datasheet are respected. The laser output power must not be increased by any means and no optics should be used with the intention of focusing the laser beam.

Figure 7. Class 1 laser product label



UM2889 - Rev 1 page 9/12



Revision history

Table 3. Document revision history

Date	Version	Changes
16-Sep-2021	1	Initial release

UM2889 - Rev 1 page 10/12



Contents

1	Overview		3
2	Doc	ument references	4
3	X-NUCLEO-53L5A1 expansion board		
	3.1	-	
	3.2	Electrical schematic	
	3.3	List of materials	6
4	VL5	3L5CX breakout board	7
5	Safety considerations		
		Electrostatic precaution	
	5.2	Laser safety considerations	9
Rev	ision	history	10



IMPORTANT NOTICE - PLEASE READ CAREFULLY

STMicroelectronics NV and its subsidiaries ("ST") reserve the right to make changes, corrections, enhancements, modifications, and improvements to ST products and/or to this document at any time without notice. Purchasers should obtain the latest relevant information on ST products before placing orders. ST products are sold pursuant to ST's terms and conditions of sale in place at the time of order acknowledgement.

Purchasers are solely responsible for the choice, selection, and use of ST products and ST assumes no liability for application assistance or the design of Purchasers' products.

No license, express or implied, to any intellectual property right is granted by ST herein.

Resale of ST products with provisions different from the information set forth herein shall void any warranty granted by ST for such product.

ST and the ST logo are trademarks of ST. For additional information about ST trademarks, please refer to www.st.com/trademarks. All other product or service names are the property of their respective owners.

Information in this document supersedes and replaces information previously supplied in any prior versions of this document.

© 2021 STMicroelectronics - All rights reserved

UM2889 - Rev 1 page 12/12