

## M24C64S-FCU Errata sheet

## M24C64S-FCU package mechanical data modifications

#### Silicon identification

This errata sheet applies to the M24C64S-FCU, that is the 64 Kbit serial I<sup>2</sup>C bus EEPROM delivered in WLCSP four balls.

Table 1 shows the list of part numbers.

Table 1. Device summary

Reference	Part Number	
M24C64S-FCU	U M24C64S-FCU6T/T, M24C64S-FCU6T/TF	

July 2016 DocID029450 Rev 1 1/10

Contents M24C64S-FCU

## **Contents**

1	M24C64S-FCU physical product change
2	Package mechanical data modifications
3	Revision history

5//

M24C64S-FCU List of tables

## List of tables

Table 1.	Device summary	1
Table 2.	D and E values corresponding to front side view	8
Table 3.	D and E values corresponding to back side view	8
Table 4.	Document revision history	9



List of figures M24C64S-FCU

# List of figures

Figure 1.	Ultra Thin WLCSP- 4-bump, 0.851 x 0.851 mm, wafer level chip scale	
	package outline	
Figure 2.	D and E front side view	
Figure 3.	D and E back side view	
Figure 4.	D or E side view	




## 1 M24C64S-FCU physical product change

There isn't any physical product change.

Figure 1 shows the package outline.

Figure 1. Ultra Thin WLCSP- 4-bump, 0.851 x 0.851 mm, wafer level chip scale package outline



The figures below show the difference between D and E dimension in the front side view (see *Figure 2*), back side (see *Figure 3*) and side view (see *Figure 4*).

Figure 2. D and E front side view





Figure 3. D and E back side view



THE PROPERTY OF THE PROPERTY O

Figure 4. D or E side view

### 2 Package mechanical data modifications

This document refers to the changes of dimensions D and E (see *Figure 3*) described in the M24C64S-FCU datasheet, in tables detailing the dimensions of the Ultra Thin WLCSP 4-bump package.

D and E values must be modified to correct the following mistake:

• The D and E values on M24C64S-FCU datasheet corresponding to front side view (ball side) as shown in *Table 2*, instead of back side view (marking side view) as shown in *Table 3*.

Table 2. D and E values corresponding to front side view

Symbol	Millimeters			Inches		
	Min	Тур	Max	Min	Тур	Max
D	-	0.833	0.853	-	0.0328	0.0336
Е	-	0.833	0.853	-	0.0328	0.0336

Table 3. D and E values corresponding to back side view

Symbol	Millimeters			Inches		
	Min	Тур	Max	Min	Тур	Max
D	0.831	0.851	0.871	0.0327	0.0335	0.0343
E	0.831	0.851	0.871	0.0327	0.0335	0.0343

The difference between back side and front side dimension is 18  $\mu$ m (0.018 mm). This difference is due to two-step sawing process, where cut 1 and cut 2 are performed with blades having different thickness (see *Figure 4* in which X represents D or E and it has the same value and tolerance).

8/10 DocID029450 Rev 1

M24C64S-FCU Revision history

## 3 Revision history

Table 4. Document revision history

Date	Revision	Changes
04-Jul-2016	1	Initial release.

#### **IMPORTANT NOTICE - PLEASE READ CAREFULLY**

STMicroelectronics NV and its subsidiaries ("ST") reserve the right to make changes, corrections, enhancements, modifications, and improvements to ST products and/or to this document at any time without notice. Purchasers should obtain the latest relevant information on ST products before placing orders. ST products are sold pursuant to ST's terms and conditions of sale in place at the time of order acknowledgement.

Purchasers are solely responsible for the choice, selection, and use of ST products and ST assumes no liability for application assistance or the design of Purchasers' products.

No license, express or implied, to any intellectual property right is granted by ST herein.

Resale of ST products with provisions different from the information set forth herein shall void any warranty granted by ST for such product.

ST and the ST logo are trademarks of ST. All other product or service names are the property of their respective owners.

Information in this document supersedes and replaces information previously supplied in any prior versions of this document.

© 2016 STMicroelectronics - All rights reserved

577